You can search for the updated part code through ITSELF web site.
URL : http://itself.sec.samsung.co.kr

3. Electrical Parts List

3-1 WS32Z10HVTXBWT

Loc. No.		Code No.	Description ; Specification	Remark
			ASSY ACCESSORY	
1		AA92-07615A	ASSY ACCESSORY;WS32Z10HFMXBWT,CIS,S58A	S.N.A
..2	CLA+CB	6002-000522	SCREW-TAPPING;TH,+,2,M4,L15,ZPC(BLK),SWR	
..2		AA68-01402A	MANUAL-GOOD WILL LETTER;,CIS,B5,1PAGE,A/	S.N.A
..2		AA69-00862A	BAG PE;-,HDPE PE FOAM,T0.03,W400,H240,-,	S.N.A
..2		AA68-02806A	MANUAL USERS;WS32Z10HVTX,XEC,Russian,Rus	S.N.A
..2		AA61-20126A	HOLDER-LEG;-,ABS,-,-,-,BLK,HB	
..2		AA68-01120A	MANUAL SERVICE;-,-,CIS,A4,6PAGE(FOLD),W/	S.N.A
..2		6801-001073	CARD-REGISTRATION;RUS,XEV,RUS,MOJO100,-,	S.N.A
..2		AA59-00307A	REMOCON;TM73,WS32Z10,S3P825AXZZ-QWRA,49,	
..2		AA68-00816B	CARD WARRANTY-01;,RUSSINA,2,W/P 120G,BOT	S.N.A
..2		AA68-00952A	CARD-COUPON;-,A/P100(G),AA68-00949A,-,-,	S.N.A
			ASSY P/MATERIAL	
1		AA92-07588A	ASSY P/MATERIAL;32Z10	S.N.A
..2		AA69-00306A	BAG AIR;LDPE,-,1800,1000,CLR,ASSY,ALL,-	S.N.A
..2		AA69-00744F	BAG-SHEET;-,HDPE PE FOAM,T0.015,W1400,H1	S.N.A
..2		AA69-00305A	BAG AIR;ALL,LDPE,1000,500,CLR,	S.N.A
..2		AA63-10007C	BAND-PP;W18,CLEA,1G	S.N.A
..2		AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A
			ASSY CHASSIS	
1		AA91-06112A	ASSY CHASSIS;WS32Z10HFMXBWT,S58A,CIS	S.N.A
..2	BR+HD	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	C/S+HD	6009-001358	SCREW-INCH MACH;BH,+,UNC3.5,L13,ZPC(YEL)	S.N.A
..2	CB+HCB	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
..2	HCB+HC	6002-000512	SCREW-TAPPING;RH,+,2,M4,L12,ZPC(BLK),SWR	S.N.A
..2	HD+H/C	6002-000512	SCREW-TAPPING;RH,+,2,M4,L12,ZPC(BLK),SWR	S.N.A
..2	MAIN	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
..2	PP+HC	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
..2	TER+HC	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2		AA94-12920A	ASSY PCB CRT;STARWAS,S58A	
...3	BOT	4715-000106	SURGE ABSORBER;300V,210-390V,-,-,AXIAL	S.N.A
...3	C522	2201-002117	C-CERAMIC,DISC;4.7nF,20%,3kV,Y5U,TP,16x6	
...3	C523	2306-000272	C-FILM,MPPF;820nF,5%,400V,BK,29x25.5x18.	
...3	CNC01	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3	CNC01A	AA39-00088A	LEAD CONNECTOR-ASSY;HERCULES,UL1007/1185	
...3	CNC02	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
...3	CNC02A	AA39-00127A	LEAD CONNECTOR-ASSY;,8P,400MM,35155-0800	
...3	GT503S	AA39-20010B	LEAD CONNECTOR-ASSY;,1P,500,YFH800-01,S,	
...3	IC501	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
....4		1201-001131	IC-VIDEO AMP;6111,SIP,9P,-,SINGLE,-,PLAS	
....4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
....4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
...3	IC502	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3	IC503	AA96-50311L	ASSY H/S;-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...3	IC504	BH99-00038E	ASSY HEAT/SINK;TDA2030,AMP,HERCULES,BH62	S.N.A
....4	CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4	CIS	1201-000010	IC-OP AMP;2030,PENTAWATT,5P,-,SINGLE,-,C	
....4	CIS	BH61-00004A	SPRING ETC-TR;CDA,CDB,SUS304,-,-,-,-,-,T	S.N.A
....4	CIS	BH62-00041A	HEAT SINK-TR;PN17LT,A1050S,T1.0,50,23,-,	S.N.A
...3	QF09	AA96-00243M	ASSY H/S;-,AMP,AA62-000450A,2SA1011,HERC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0502-000131	TR-POWER;2SA1011-D,PNP,1.2W,TO-220,-,60	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	QF10	AA96-00243L	ASSY H/S;-,CRT,AA62-000450A,2SC2344,HERC	S.N.A
....4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4		0502-000153	TR-POWER;2SC2344-D,NPN,1.2W,TO-220,-,60	
....4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
...3	R529	2008-000264	R-FUSIBLE(S);1ohm,5%,1W,AF,TP,3.9x10mm	
...3	SC01	3722-001503	JACK-PIN;1P,1PI,NI,RED,SCR-JACK	
⚠ ...3	V999S	3704-001032	SOCKET-CRT;8P,29PI,35.5PI,AU30U	
...3		AA97-12040A	ASSY AUTO-CRT;CS29Z6HP,K55A	S.N.A
....4	C501	2201-000193	C-CERAMIC,DISC;0.01NF,0.25PF,50V,C0G,TP,	
....4	C504	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C505	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C506	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C507	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C508	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C509	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm	
....4	C510	2201-000291	C-CERAMIC,DISC;1NF,10%,500V,Y5P,TP,7.5X3	
....4	C511	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C512	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C513	2201-000600	C-CERAMIC,DISC;0.56NF,10%,50V,Y5P,TP,5X3	
....4	C514	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C515	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C520	2401-000703	C-AL;2200uF,20%,25V,GP,-,12.5x25mm,	
....4	C526	2301-001211	C-FILM,PPF;22nF,5%,400V,TP,20x7x14,7.5mm	
....4	C528	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C531	2401-002264	C-AL;10uF,20%,350V,GP,TP,10x20mm,5m	
....4	C532	2401-001563	C-AL;47uF,20%,400V,GP,TP,16x25,7.5	
....4	C533	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4	C534	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	C535	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
....4	CF01	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
....4	CF02	2201-000017	C-CERAMIC,DISC;1NF,10%,50V,Y5P,TP,5X3.5M	
....4	CF03	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
....4	CF04	2201-000516	C-CERAMIC,DISC;4.7NF,+100-0%,500V,Y5U,TP	
....4	CF05	2301-000261	C-FILM,PEF;4.7nF,5%,100V,TP,10.5x12.5x6.	
....4	CF06	2201-000192	C-CERAMIC,DISC;0.01NF,0.25PF,500V,C0G,TP	
....4	CF07	2201-000604	C-CERAMIC,DISC;0.056NF,+100-0%,500V,SL,T	
....4	CF71	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4	CF73	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
....4	CF74	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4	CF75	2401-000045	C-AL;10uF,20%,160V,GP,TP,10x16,5	
....4	D501	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	D502	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D509	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D510	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D511	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D512	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D513	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	D514	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DF01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF02	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF05	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF06	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4	DF07	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DF08	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4	DZ501	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
....4	DZ502	0403-000708	DIODE-ZENER;MTZJ13B,13V,12.55-13.21V,500	
....4	DZ504	0403-000698	DIODE-ZENER;TZP12A,12V,11.4-12.6V,1W,DO-	
....4	DZ510	0403-000734	DIODE-ZENER;TZP15B,15V,14.7-16.5V,1W,DO-	
....4	DZF01	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	

Loc. No.	Code No.	Description ; Specification	Remark
....4 DZF02	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,T	
....4 DZF03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4 EL100	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL80	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL81	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL82	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL83	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL84	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL85	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL86	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL87	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL88	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL89	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL92	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL94	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL95	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL96	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL97	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL98	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL99	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 FN1	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
....4 FV1	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
....4 GT501	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT502	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT503	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT504	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 L502	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
....4 LF01	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 LF02	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 LF03	2701-000112	INDUCTOR-AXIAL;100uH,10%,3x7mm	
....4 LF04	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 LF06	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 LF08	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 LF09	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 LF11	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 PCB	AA41-00578D	PCB-CRT;CT-29Z7HR,FR-1,1L,D,1.6T,330X245	S.N.A
....4 Q501	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4 Q502	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4 Q503	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4 Q504	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4 QF02	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 QF03	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 QF04	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4 QF05	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 R501	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R502	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R503	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 R504	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R505	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R506	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R507	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R508	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R509	2008-001047	R-FUSIBLE(S);68ohm,5%,2W,AF,TP,3.9x10mm	
....4 R510	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R511	2001-001194	R-CARBON(S);82KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R512	2004-001369	R-METAL(S);1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
....4 R513	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4 R514	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4 R515	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
....4 R516	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 R518	2001-001095	R-CARBON(S);2.2MOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R519	2001-000356	R-CARBON;150KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R520	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R522	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R523	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R525	2002-001006	R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.7	
....4 R527	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R528	2003-000458	R-METAL OXIDE(S);100ohm,5%,2W,AF,TP,4x12	
....4 R530	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R531	2001-000539	R-CARBON;24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R540	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R541	2008-001053	R-FUSIBLE;22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
....4 R554	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R555	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R556	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R560	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R561	2001-001126	R-CARBON(S);300OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R562	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R563	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R564	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R565	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R566	2001-001040	R-CARBON(S);0.68OHM,5%,1/2W,AA,TP,2.4X6.	
....4 RF13	2008-001053	R-FUSIBLE;22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
....4 RF14	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4 RF15	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4 RF16	2003-002276	R-METAL OXIDE(S);2.2KOHM,5%,2W,AG,TP,12X	
....4 RF17	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 RF18	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 RF19	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 RF20	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RF21	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RF22	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RF23	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RF24	2003-001018	R-METAL OXIDE(S);220ohm,5%,2W,AF,TP,3.9x	
....4 RF25	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RF26	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 RF27	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 RF28	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RF29	2001-001071	R-CARBON(S);12KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 RF30	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RF31	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RF32	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4 RF33	2001-001053	R-CARBON(S);1.5OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 RF34	2001-001100	R-CARBON(S);2.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 RF35	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4 RF36	2003-000652	R-METAL OXIDE(S);330ohm,5%,2W,AF,TP,4x12	
...3	0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2	AA94-12862A	ASSY PCB MISC-SUB POWR;,S58A,32Z10,CIS P	
...3 BS+H/D	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
...3 C823	2401-002213	C-AL;150uF,+30-10%,450V,GP,BK,25x35	
...3 CND801	3711-000974	CONNECTOR-HEADER;BOX,4P,1R,5.08mm,STRAIG	
...3 CND802	3711-000164	CONNECTOR-HEADER;1WALL,2P,1R,2.5mm,STRAI	S.N.A
⚠ ...3 CND803	AA39-20067B	LEAD CONNECTOR-ASSY;,10P,200,YBNH025-10,	
⚠ ...3 D801S	0402-000102	DIODE-BRIDGE;D2SB60,600V,1.5A,-	
...3 DD817	AA96-00111C	ASSY H/S;-,-,AA62-30013L,FML-G12S,-	S.N.A
....4	0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
....4	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	AA62-30013L	HEAT SINK-ES;-,-,-,-,44/22,-,WHT,-,-,-,-	S.N.A
...3 FANBSF	6003-001495	SCREW-TAPTITE;PH,+,S,M3,L20,ZPC(BLK),SWR	
⚠ ...3 IC801S	AA96-50406H	ASSY H/S;AA62-30180K,SCREW,5Q0765RT,OIL	S.N.A
....4 CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4 CIS	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4 CIS	AA62-30180K	HEAT SINK-ES;-,A6063 EXTR,-,WHT,50/13,-,	S.N.A
....4 CIS	1203-001932	IC-PWM CONTROLLER;5Q0765,TO-220F,5P,185M	
...3 ICD81	1203-002139	IC-POSI.FIXED REG.;378R12,TO-220F,4P,393	
...3 ICD82	1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
...3 ICD83	AA96-00111P	ASSY H/S;-,MAIN,AA62-30013L,KA278RA05,FA	S.N.A
....4	1203-001978	IC-VOLTAGE REGULATOR;KA278RA05,TO-220F,4	
....4	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	AA62-30013L	HEAT SINK-ES;-,-,-,-,44/22,-,WHT,-,-,-,-	S.N.A
...3 LD816	AA27-00119A	COIL CHOKE;10uH,-,10uH,10%,0.07,0.1ohm M	
...3 LD817	AA27-00119A	COIL CHOKE;10uH,-,10uH,10%,0.07,0.1ohm M	
⚠ ...3 NT821S	1404-001195	THERMISTOR-NTC;5.1ohm,15%,2900,27mW/C,BK	
⚠ ...3 PC821S	0604-001032	PHOTO-COUPLER;TR,170-260%,300mW,DIP-4,ST	
...3 RD822	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ ...3 RL801S	3501-001053	RELAY-POWER;5VDC,530MW,10000MA,1FORMA,15	
...3 S/B+HD	6002-000512	SCREW-TAPPING;RH,+,2,M4,L12,ZPC(BLK),SWR	S.N.A
...3 S/P+HD	6002-000512	SCREW-TAPPING;RH,+,2,M4,L12,ZPC(BLK),SWR	S.N.A
⚠ ...3 TD801S	AA26-00203A	TRANS SWITCHING;EER3543,WS32Z10,160~300V	
...3	0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3	AA39-00283A	LEAD CONNECTOR-ASSY;VC1A,UL1007#18,UL/CS	
...3	AA97-13759A	ASSY AUTO-SUB POWER;32Z10,S58A,EROPE	S.N.A
....4 0	AA41-00875A	PCB-SUB_POWER;WS32Z10,FR-1,1L,A,1.6,T,S5	S.N.A
....4 C802	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5	
....4 C803	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C804	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4 C805	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,	
....4 C806	2201-000984	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
....4 C821	2201-000315	C-CERAMIC,DISC;2.2NF,+80-20%,250V,Y5U,TP	
....4 C822	2201-000315	C-CERAMIC,DISC;2.2NF,+80-20%,250V,Y5U,TP	
....4 CD811	2201-000551	C-CERAMIC,DISC;0.47NF,10%,1KV,Y5P,TP,6.3	
....4 CD812	2401-000698	C-AL;2200uF,20%,16V,WT,TP,12.5x25,5	
....4 CD813	2401-000133	C-AL;1000uF,20%,16V,GP,TP,10x20,5	
....4 CD814	2401-000142	C-AL;1000uF,20%,16V,WT,TP,10x20,5	

Loc. No.	Code No.	Description ; Specification	Remark
....4 CD816	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 CD817	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
....4 CD818	2201-000551	C-CERAMIC,DISC;0.47NF,10%,1KV,Y5P,TP,6.3	
....4 CD819	2401-000384	C-AL;10uF,20%,100V,GP,TP,6.3x11,5mm	
....4 CD821	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 CD822	2201-000551	C-CERAMIC,DISC;0.47NF,10%,1KV,Y5P,TP,6.3	
....4 CD823	2401-000142	C-AL;1000uF,20%,16V,WT,TP,10x20,5	
....4 CD824	2401-000142	C-AL;1000uF,20%,16V,WT,TP,10x20,5	
....4 CD825	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
....4 CD826	2201-000551	C-CERAMIC,DISC;0.47NF,10%,1KV,Y5P,TP,6.3	
....4 CD827	2401-000689	C-AL;2200uF,20%,16V,GP,TP,13x25,5	
....4 CD828	2401-000142	C-AL;1000uF,20%,16V,WT,TP,10x20,5	
....4 CD829	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 CD831	2301-000010	C-FILM,PEF;100nF,5%,100V,TP,11.5x12.5mm,	
....4 CD832	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 CD836	2401-000493	C-AL;10uF,20%,50V,LZ,TP,5x11mm,5mm	
⚠ 4 D803	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
⚠ 4 D804	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4 DD811	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
....4 DD813	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4 DD815	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
....4 DD818	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4 DZ801	0403-001140	DIODE-ZENER;RD10ESAB-T4,10V,9.19-10.30V,	
....4 DZ802	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500mW,DO	
....4 DZ803	0403-000699	DIODE-ZENER;TZP27B,27V,27-30.8V,1W,DO-41	
....4 DZ804	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4 DZ805	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
....4 EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL803	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL804	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EY811	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY812	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY813	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY814	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY815	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY816	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY817	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY818	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY819	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY820	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY821	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY822	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY823	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY824	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY825	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY826	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 GT801	AA60-40012A	PIN-GT,ASSY;T1.6,1P	S.N.A
....4 GT802	AA60-40012A	PIN-GT,ASSY;T1.6,1P	S.N.A
....4 GT803	AA60-40012A	PIN-GT,ASSY;T1.6,1P	S.N.A
....4 ICD812	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
....4 L802	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4 L803	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4 QD801	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
....4 R805	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R808	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R823	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4 R824	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4 R831	2001-001192	R-CARBON(S);820OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R840	2001-001055	R-CARBON(S);1.8KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R843	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 R844	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4 R850	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 RD801	2008-001058	R-FUSIBLE;0.18ohm,5%,1W,AF,TP,3.9x10mm	
....4 RD802	2008-001058	R-FUSIBLE;0.18ohm,5%,1W,AF,TP,3.9x10mm	
....4 RD803	2008-001058	R-FUSIBLE;0.18ohm,5%,1W,AF,TP,3.9x10mm	
....4 RD804	2008-001058	R-FUSIBLE;0.18ohm,5%,1W,AF,TP,3.9x10mm	
....4 RD811	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 RD812	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RD813	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RD814	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 RD815	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
....4 RD816	2001-001072	R-CARBON(S);12OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 RD821	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RD823	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RD825	2001-001144	R-CARBON(S);4.7KOHM,5%,1/2W,AA,TP,2.4X6.	
...3	MD31-00001A	FAN;,G6015S12B-RH,PBTP,ASSY(400MM LENGTH	

Loc. No.	Code No.	Description ; Specification	Remark
...3	AA61-01174A	BRACKET-SUB,FAN;B3K,SECC,T1.0	S.N.A
...3	AA61-01290A	HOLDER-DVR;32Z10,HIPS V0,BLK	S.N.A
..2	AA94-12615A	ASSY PCB MISC-TERMINAL BOARD;32Z10,S58A,	
...3 PCB+TB	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
...3	AA94-08526C	ASSY PCB MISC-DOLBY TERMINAL;32Z6,S57A	
....4 CNE703	AA39-20461C	LEAD CONNECTOR-ASSY;,11P,300MM,YBNH250-1	
....4 CNE704	AA39-20068D	LEAD CONNECTOR-ASSY;,8P,300,YBNH025-08,6	
....4 JE707	3722-001546	JACK-PIN;3P,3.5mm,AU,WHT/RED/BLK,-	
....4 JE708	3722-001546	JACK-PIN;3P,3.5mm,AU,WHT/RED/BLK,-	
....4 JE709	0603-001068	OPTIC TRANSMITTER;5V,6Mb/s,5m,-15dBm,660	
....4 JE710	3722-001546	JACK-PIN;3P,3.5mm,AU,WHT/RED/BLK,-	
....4	0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
....4	AA97-13507A	ASSY AUTO-DOLBY TERMINAL;32Z9,32Z7,S57A	S.N.A
.....5 CE706	2202-000145	C-CERAMIC,MLC-AXIAL;0.12NF,10%,50V,Y5P,T	
.....5 CE707	2202-000145	C-CERAMIC,MLC-AXIAL;0.12NF,10%,50V,Y5P,T	
.....5 CE708	2202-000145	C-CERAMIC,MLC-AXIAL;0.12NF,10%,50V,Y5P,T	
.....5 CE709	2202-000145	C-CERAMIC,MLC-AXIAL;0.12NF,10%,50V,Y5P,T	
.....5 CE710	2202-000145	C-CERAMIC,MLC-AXIAL;0.12NF,10%,50V,Y5P,T	
.....5 CE711	2202-000145	C-CERAMIC,MLC-AXIAL;0.12NF,10%,50V,Y5P,T	
.....5 CE712	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
.....5 CE713	2401-000486	C-AL;10uF,20%,50V,GP,TP,6.3x7mm,5	
.....5 CE714	2202-000145	C-CERAMIC,MLC-AXIAL;0.12NF,10%,50V,Y5P,T	
.....5 CE715	2202-000145	C-CERAMIC,MLC-AXIAL;0.12NF,10%,50V,Y5P,T	
.....5 DE701	0403-000718	DIODE-ZENER;MTZJ6.8B,6.8V,6.49-6.83V,500	
.....5 LE706	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5 LE707	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5 LE708	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5 LE709	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5 LE710	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5 LE711	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5 LE712	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5 LE713	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5 LE714	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
.....5 PCB	AA41-00650A	PCB-DOLBY TERMINAL;CS29Z7HF,FR-1,1L,A,1.	S.N.A
.....5 RE701	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5 RE702	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5 RE703	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5 RE704	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	AA94-12600A	ASSY PCB MISC-A/V TERMINAL;AV/TERMINAL,S	
....4 CNE701	AA39-20071D	LEAD CONNECTOR-ASSY;,12P,300,YBNH025-12,	
....4 CNE702	AA39-20112E	LEAD CONNECTOR-ASSY;,9P,300,YBNH025-09,6	
....4 JE701	AA63-40258A	TERMINAL-SPEAKER;4P,ABS,4,BLK	S.N.A
....4 JE703	3722-001632	JACK-PIN;1P,-,NI,BLK,-	
....4 JE704	3722-001547	JACK-PIN;3P,3.5mm,AU,GRN/BLU/RED,-	
....4 JE705	3722-000212	JACK-MODULAR;8P/8C,INVERTED,N,ANGLE,STAN	
....4	AA97-13757A	ASSY AUTO-A/V TERMINAL;32Z10,S58A	S.N.A
.....5 0	AA41-00877A	PCB-AV_TERMINAL;WS32Z10,FR-1,1,A,1.6,T,S	S.N.A
.....5 CE701	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
.....5 CE702	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
.....5 CE703	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
.....5 CE704	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
.....5 CE705	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
.....5 CE706	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
.....5 CE707	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
.....5 DE701	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
.....5 LE701	2701-001027	INDUCTOR-AXIAL;1uH,10%,4.5x14mm	
.....5 LE702	2701-001027	INDUCTOR-AXIAL;1uH,10%,4.5x14mm	
.....5 LE703	2701-001027	INDUCTOR-AXIAL;1uH,10%,4.5x14mm	
.....5 LE704	2701-001027	INDUCTOR-AXIAL;1uH,10%,4.5x14mm	
.....5 LE705	2701-001027	INDUCTOR-AXIAL;1uH,10%,4.5x14mm	
.....5 RE701	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
.....5 RE702	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4	0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3	AA96-01352B	ASSY COVER P-TERMINAL BOARD;WS32Z10,CIS,	S.N.A
....4	AA64-03365A	INLAY-TERMINAL,BOARD;32Z10,PS SHEET,T0.3	S.N.A
....4	AA65-00033A	TERMINAL-BOARD,ANT;,HIPS V0,BLK	S.N.A
..2	AA94-12599A	ASSY PCB MISC-LED;LED,S58A,32Z10,PAL(EUR	
...3 CN02	AA39-20055D	LEAD CONNECTOR-ASSY;,6P,400,YBNH025-06,6	
...3 LD01	0601-001381	LED;ROUND,RED/GRN,5.0MM,650/563NM	
...3 RM01	AA32-00012A	MODULE REMOCON;ORC-50HF2,38KHZ,940NM,MES	
...3	AA97-13756A	ASSY AUTO-LED;32Z10,S58A,PAL(EROPE)	S.N.A
....4 0	AA41-00876A	PCB-LED;WS32Z10,FR-1,1,A,1.6,T,S58A,16A,	S.N.A
....4 CY01	2401-002009	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
....4 DC01	0403-000719	DIODE-ZENER;MTZJ7.5B,7.5V,7.07-7.45V,500	
....4 RY01	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 RY03	2001-001111	R-CARBON(S);240OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 RY04	2001-001111	R-CARBON(S);240OHM,5%,1/2W,AA,TP,2.4X6.4	

Loc. No.		Code No.	Description ; Specification	Remark
...3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2		AA96-01476A	ASSY COVER P-BRACKET;WS32Z10,CIS,SEEC T1	S.N.A
...3		AA61-01295A	BRACKET-HDD;32Z10,SECC,T1.0	S.N.A
...3		MD60-00003A	SPACER-RUBBER;SM-C30,NEOPRENE HB,GRAY	S.N.A
⚠ ..2		AA96-20130B	ASSY POWER CORD;-,CP2/NO(4.0R),H/C400MM,	S.N.A
..2		MD63-00007A	COVER-SCREW;SM-C20.30,BSBM,T1.0	S.N.A
..2		AA59-00301A	HDD;40GB,SV4012H,S63,H16,C16143,H25.4MM,	
..2		AA94-12611A	ASSY PCB MISC-DVR;WS32Z10HF,S58A	
...3	CN101	3711-002641	CONNECTOR-HEADER;BOX,10P,1R,2.5MM,STRAIG	
...3	CN102	3711-005032	CONNECTOR-HEADER;BOX,32P,2R,2MM,ANGLE ,S	
...3	CN302	3711-000919	CONNECTOR-HEADER;BOX,40P,2R,2.54mm,STRAI	
...3	CN303	3711-000019	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH	S.N.A
...3	CN401	3711-001465	CONNECTOR-HEADER;NOWALL,3P,1R,2.54mm,STR	
...3	IC405	1102-001090	IC-EPROM;27C801,1MX8BIT,DIP,32P,600MIL,1	
...3	P301	1404-001039	THERMISTOR-NTC;10Kohm,1%,3435K,2.1mW/C,B	
...3	PD+S/B	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
...3	SW401	3404-000178	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	X401	2801-003224	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAY,12.5	
...3		AA39-00253E	LEAD CONNECTOR;STATWARS,UL2651#28,40P,10	
...3		AA63-00659A	SHIELD-DVR,BOT;32Z10,SPTE,T0.5	S.N.A
...3		AA63-00658A	SHIELD-DVR,TOP;32Z10,SPTE,T0.5	S.N.A
...3		AA97-13741A	ASSY SMD;WS32Z10HF,S58A	S.N.A
....4	0	AA41-00850A	PCB-DVR;WS32Z78RMX,FR-4,4L,A,1.6T,190X19	S.N.A
....4	C101	2402-001033	C-AL,SMD;220uF,20%,16V,GP,TP,8.3x8.3x10	
....4	C102	2402-001033	C-AL,SMD;220uF,20%,16V,GP,TP,8.3x8.3x10	
....4	C103	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C104	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C105	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
....4	C106	2402-001033	C-AL,SMD;220uF,20%,16V,GP,TP,8.3x8.3x10	
....4	C107	2402-001033	C-AL,SMD;220uF,20%,16V,GP,TP,8.3x8.3x10	
....4	C108	2402-001033	C-AL,SMD;220uF,20%,16V,GP,TP,8.3x8.3x10	
....4	C109	2402-001033	C-AL,SMD;220uF,20%,16V,GP,TP,8.3x8.3x10	
....4	C110	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C111	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C112	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C113	2402-001033	C-AL,SMD;220uF,20%,16V,GP,TP,8.3x8.3x10	
....4	C114	2402-001033	C-AL,SMD;220uF,20%,16V,GP,TP,8.3x8.3x10	
....4	C115	2402-001033	C-AL,SMD;220uF,20%,16V,GP,TP,8.3x8.3x10	
....4	C118	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	C119	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C120	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C121	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C122	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C124	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C126	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
....4	C128	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C129	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	C130	2203-000552	C-CERAMIC,CHIP;0.02NF,5%,50V,C0G,TP,1608	
....4	C131	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
....4	C132	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
....4	C133	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
....4	C134	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	C135	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C136	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C137	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4,	
....4	C139	2203-001652	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,TP,	
....4	C140	2203-001652	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,TP,	
....4	C141	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
....4	C142	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
....4	C143	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4,	
....4	C144	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C145	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C146	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
....4	C147	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C148	2203-000552	C-CERAMIC,CHIP;0.02NF,5%,50V,C0G,TP,1608	
....4	C149	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
....4	C151	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
....4	C152	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
....4	C153	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
....4	C154	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
....4	C155	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
....4	C156	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
....4	C158	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C159	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C160	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C161	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C162	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C163	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C164	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C165	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C166	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C167	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C168	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C169	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C170	2203-000384	C-CERAMIC,CHIP;0.015NF,5%,50V,C0G,TP,160	
....4	C171	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
....4	C172	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	C173	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
....4	C174	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
....4	C175	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
....4	C176	2402-001033	C-AL,SMD;220uF,20%,16V,GP,TP,8.3x8.3x10	
....4	C178	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C179	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
....4	C180	2402-001033	C-AL,SMD;220uF,20%,16V,GP,TP,8.3x8.3x10	
....4	C181	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C201	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	C202	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C203	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C204	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C205	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C206	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C207	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C208	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C209	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	C210	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C211	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C212	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C213	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C214	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C215	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C216	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C217	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	C218	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C219	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C220	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C221	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C222	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C223	2203-000384	C-CERAMIC,CHIP;0.015NF,5%,50V,C0G,TP,160	
....4	C224	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	C225	2203-000384	C-CERAMIC,CHIP;0.015NF,5%,50V,C0G,TP,160	
....4	C226	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C227	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C228	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C229	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C230	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C231	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
....4	C232	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	C233	2203-000384	C-CERAMIC,CHIP;0.015NF,5%,50V,C0G,TP,160	
....4	C234	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C235	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C236	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
....4	C301	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C302	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	C303	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	C304	2203-000384	C-CERAMIC,CHIP;0.015NF,5%,50V,C0G,TP,160	
....4	C305	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C306	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C313	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	C314	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C317	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
....4	C318	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
....4	C319	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
....4	C320	2203-001656	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,1608	
....4	C322	2203-001656	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,1608	
....4	C323	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4,	
....4	C324	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C326	2203-001656	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,1608	
....4	C327	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4,	
....4	C328	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C329	2203-001656	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,1608	
....4	C330	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4	C331	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4	C332	2402-000144	C-AL,SMD;3.3uF,20%,50V,GP,TP,4.3x4.3x5.	
....4	C333	2402-000144	C-AL,SMD;3.3uF,20%,50V,GP,TP,4.3x4.3x5.	

Loc. No.	Code No.	Description ; Specification	Remark
....4 C334	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C335	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C337	2203-000140	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,1608	
....4 C339	2203-000140	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,1608	
....4 C340	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C341	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C342	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4 C401	2203-006170	C-CERAMIC,CHIP;220NF,10%,16V,X7R,TP,1608	
....4 C402	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C403	2203-000384	C-CERAMIC,CHIP;0.015NF,5%,50V,C0G,TP,160	
....4 C404	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4 C405	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C406	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C407	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C408	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C409	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C410	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C411	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C412	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4 C413	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C414	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C415	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C416	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C417	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C418	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C419	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4 C420	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C421	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C422	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C423	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C424	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C425	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C426	2203-000384	C-CERAMIC,CHIP;0.015NF,5%,50V,C0G,TP,160	
....4 C427	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4 C428	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C429	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C430	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C431	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C432	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C433	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C434	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C435	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C436	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C437	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C438	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C439	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C440	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C441	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4 C442	2203-000384	C-CERAMIC,CHIP;0.015NF,5%,50V,C0G,TP,160	
....4 C443	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C445	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C448	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4 C449	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C450	2203-000041	C-CERAMIC,CHIP;0.01NF,0.25PF,50V,C0G,TP,	
....4 C451	2203-000041	C-CERAMIC,CHIP;0.01NF,0.25PF,50V,C0G,TP,	
....4 C453	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4 C454	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C455	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
....4 C456	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C457	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
....4 C460	2203-000384	C-CERAMIC,CHIP;0.015NF,5%,50V,C0G,TP,160	
....4 EF102	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 EF103	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 EF104	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 EF105	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 EF106	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 EF107	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 EF108	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 EF109	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 EF110	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 EF111	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 EF112	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 EF113	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 EF114	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 EF115	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 EF116	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M	
....4 IC102	1205-001606	IC-BUFFER;CY2305SC-1H,SOIC,8P,150MIL,PLA	

Loc. No.	Code No.	Description ; Specification	Remark
....4 IC104	1204-002058	IC-VIDEO DECODER;SAA7115HL,LQFP,100P,14X	
....4 IC105	1209-001333	IC-PLL/SYNTHESISER;MK2703,SOP,8P,150MIL,	
....4 IC106	1002-001332	IC-A/D CONVERTER;CS5333-KZ,24BIT,TSSOP,1	
....4 IC201	1204-002091	IC-ENCODER;ES7010F,PQFP,208P,28X28MM,PLA	S.N.A
....4 IC202	1105-001305	IC-DRAM;4S641632,1Mx16x4Bit,TSOP,54P,400	
....4 IC203	1105-001305	IC-DRAM;4S641632,1Mx16x4Bit,TSOP,54P,400	
....4 IC301	0801-002814	IC-CMOS LOGIC;SN74LVC138ADR,3-of-8 DECOD	
....4 IC302	1301-001478	IC-CPLD;2032,TQFP,44P,-,10nS,3.3V,10%,80	
....4 IC303	0801-002268	IC-CMOS LOGIC;74VHC139,DECODER,SOIC,16P,	
....4 IC308	1002-001227	IC-D/A CONVERTER;CS4340-KSR,24BIT,SOP,16	
⚠ 4 IC401	1204-002117	IC-DECODER;ES6028F,PQFP,208,28x28mm,PLAS	
⚠ 4 IC402	1105-001305	IC-DRAM;4S641632,1Mx16x4Bit,TSOP,54P,400	
⚠ 4 IC404	0909-001039	IC-REAL TIME CLOCK;X1226S8,SOIC,8,4.0x5.	
⚠ 4 IC406	1103-000129	IC-EEPROM;24C02,256x8BIT,SOP,8P,150MIL,1	
....4 IQ101	1203-001359	IC-POSI.FIXED REG.;1086,TO-263,3P,15.8MM	
....4 IQ102	1203-001359	IC-POSI.FIXED REG.;1086,TO-263,3P,15.8MM	
....4 IQ103	1203-002351	IC-VOLTAGE REGULATOR;LF25C,DPAK,3P,240MI	
....4 IQ104	1203-001198	IC-POSI.ADJUST REG.;1086,DDPAC,3P,400MIL	
....4 IQ105	1203-001198	IC-POSI.ADJUST REG.;1086,DDPAC,3P,400MIL	
....4 IQ401	1203-001211	IC-VOL. DETECTOR;7027,SOT-89,3P,-,PLASTI	
....4 L101	3301-001202	CORE-FERRITE BEAD;AB,120ohm,4.5x3.2x1.3m	
....4 L102	3301-001202	CORE-FERRITE BEAD;AB,120ohm,4.5x3.2x1.3m	
....4 L103	3301-001202	CORE-FERRITE BEAD;AB,120ohm,4.5x3.2x1.3m	
....4 L104	3301-001202	CORE-FERRITE BEAD;AB,120ohm,4.5x3.2x1.3m	
....4 L105	3301-001202	CORE-FERRITE BEAD;AB,120ohm,4.5x3.2x1.3m	
....4 L106	3301-001202	CORE-FERRITE BEAD;AB,120ohm,4.5x3.2x1.3m	
....4 L107	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L109	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L110	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L111	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L112	2703-000125	INDUCTOR-SMD;10uH,10%,1.25x2x1.25mm	
....4 L113	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L201	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L202	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L203	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L204	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L205	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L206	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L207	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L301	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L302	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L304	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L305	2703-000274	INDUCTOR-SMD;2.2uH,10%,1.25x2x0.85mm	
....4 L307	2703-000274	INDUCTOR-SMD;2.2uH,10%,1.25x2x0.85mm	
....4 L309	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L310	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
⚠ 4 L401	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
⚠ 4 L402	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
⚠ 4 L403	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L404	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L405	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L407	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L408	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 L409	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
....4 R101	2007-000766	R-CHIP;330OHM,5%,1/10W,DA,TP,2012	
....4 R102	2007-001092	R-CHIP;620OHM,5%,1/10W,DA,TP,2012	
....4 R108	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R109	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R110	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R114	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R115	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R119	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R120	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R124	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R125	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R126	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R127	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
....4 R128	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
....4 R129	2007-001133	R-CHIP;68OHM,5%,1/10W,DA,TP,2012	
....4 R131	2007-001133	R-CHIP;68OHM,5%,1/10W,DA,TP,2012	
....4 R132	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
....4 R134	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
....4 R135	2007-000402	R-CHIP;150ohm,5%,1/16W,DA,TP,1608	
....4 R136	2007-000402	R-CHIP;150ohm,5%,1/16W,DA,TP,1608	
....4 R138	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
....4 R139	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R140	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	

Loc. No.	Code No.	Description ; Specification	Remark
....4 R141	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
....4 R142	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R143	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
....4 R144	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
....4 R145	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R146	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R147	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R148	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R149	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4 R150	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
....4 R151	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R152	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R153	2007-001134	R-CHIP;68ohm,5%,1/16W,DA,TP,1608	
....4 R154	2007-001134	R-CHIP;68ohm,5%,1/16W,DA,TP,1608	
....4 R155	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R156	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R157	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R159	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R160	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R161	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4 R162	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
....4 R163	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
....4 R201	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
....4 R202	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R203	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4 R204	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R205	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R206	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4 R207	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4 R208	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R209	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R210	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R213	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R301	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4 R302	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4 R303	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R304	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R305	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R306	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R307	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R308	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R309	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4 R310	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
....4 R311	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
....4 R312	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4 R313	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4 R316	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R319	2007-000277	R-CHIP;100KOHM,1%,1/10W,DA,TP,2012	
....4 R320	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R321	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R322	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
....4 R323	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R324	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R325	2007-000071	R-CHIP;22ohm,5%,1/16W,DA,TP,1608	
....4 R326	2007-000071	R-CHIP;22ohm,5%,1/16W,DA,TP,1608	
....4 R327	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R329	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
....4 R330	2007-001166	R-CHIP;75OHM,5%,1/10W,DA,TP,2012	
....4 R332	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
....4 R335	2007-001166	R-CHIP;75OHM,5%,1/10W,DA,TP,2012	
....4 R336	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4 R337	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
....4 R338	2007-000119	R-CHIP;560ohm,5%,1/16W,DA,TP,1608	
....4 R339	2007-000119	R-CHIP;560ohm,5%,1/16W,DA,TP,1608	
....4 R342	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R346	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R347	2007-000297	R-CHIP;10KOHM,1%,1/10W,DA,TP,2012	
....4 R401	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
....4 R402	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
....4 R405	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
....4 R407	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
....4 R412	2007-000100	R-CHIP;68Kohm,5%,1/16W,DA,TP,1608	
....4 R413	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
....4 R414	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R415	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
....4 R416	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R417	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R418	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R419	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R420	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R421	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
....4 R422	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
....4 R423	2007-000113	R-CHIP;33ohm,5%,1/16W,DA,TP,1608	
....4 R424	2007-000642	R-CHIP;270OHM,5%,1/10W,DA,TP,2012	
....4 R427	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R428	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R429	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R430	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R431	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R432	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
....4 R433	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R434	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 R435	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
....4 RW101	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW102	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW201	2011-000817	R-NETWORK;10Kohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW202	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW203	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW204	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW205	2011-000817	R-NETWORK;10Kohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW206	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW207	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW208	2011-000817	R-NETWORK;10Kohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW209	2011-000817	R-NETWORK;10Kohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW210	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW211	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW212	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW213	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW214	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW215	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW216	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW217	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW218	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW219	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW220	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW301	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW302	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW303	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW304	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW305	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW306	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW307	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW308	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW401	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW402	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW403	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW404	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW405	2011-000881	R-NETWORK;33ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW406	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW407	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW408	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW409	2011-000651	R-NETWORK;10ohm,5%,63mW,L,CHIP,8P,TP	
....4 RW410	2011-001193	R-NETWORK;68ohm,5%,1/16W,L,CHIP,8P,TP	
....4 RW411	2011-000585	R-NETWORK;47ohm,5%,63mW,L,CHIP,8P,TP	
....4 X101	2804-001521	OSCILLATOR-CLOCK;27MHZ,50PPM,HCMOS,TP,3.	
....4 X103	2801-003804	CRYSTAL-SMD;24.576MHZ,30PPM,28-AAN,20PF,	
..2	AA61-01102A	HOLDER-CHASSIS;Z7,HIPS V0,G4309	S.N.A
..2	AA61-01105A	HOLDER-C,BLOCK;Z7,HIPS V0,G4309	S.N.A
..2	AA65-00011B	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
..2	AA94-12593A	ASSY PCB MAIN;WS32Z10HFMXBWT,S58A	
...3 C-BLOC	AA26-00069A	TRANS FBT;FUJ-29C002C(S),DREAM3,4,-,-,-,	
...3 C/W	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-,	S.N.A
...3 CJ701A	3722-000195	JACK-SCART;42P,-,SN,BLK,NO	
...3 CJ704A	3722-000183	JACK-SCART;21P,4mm,SN,BLK,NO	
...3 CN501A	3711-003241	CONNECTOR-HEADER;BOX,14P,1R,2.5MM,STRAIG	
...3 CN601A	3711-003043	CONNECTOR-HEADER;BOX,4P,1R,2.5MM,STRAIGH	
...3 CN602A	3711-000628	CONNECTOR-HEADER;BOX,11P,1R,2.5MM,STRAIG	
...3 CN603A	AA39-20052A	LEAD CONNECTOR-ASSY;,4P,300,YBNH025-04,Y	
...3 CN604A	3711-003641	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3 CN605A	AA39-00094A	LEAD CONNECTOR-ASSY;,3(2)P,200MM,YBNH250	
...3 CN702A	3711-003641	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
...3 CN804A	3711-003241	CONNECTOR-HEADER;BOX,14P,1R,2.5MM,STRAIG	
...3 CNC904	AA39-00242B	LEAD CONNECTOR;S57A/WS32Z78RMX,UL1007#26	
...3 CND01	3711-003136	CONNECTOR-HEADER;BOX,32P,2R,2MM,STRAIGHT	

Loc. No.	Code No.	Description ; Specification	Remark
...3 CND01A	BP39-00024A	LEAD CONNECTOR;L62A/HLM507W,UL1185#26,UL	
...3 CW901A	3703-001150	CONNECTOR-BACK PANEL;32P,2R,FEMALE,STRAI	
...3 CW902A	3703-001150	CONNECTOR-BACK PANEL;32P,2R,FEMALE,STRAI	
...3 GTAY01	AA39-20179C	LEAD CONNECTOR-ASSY;,3(2)P,600MM,YFH800-	
...3 GTAY02	AA39-20179C	LEAD CONNECTOR-ASSY;,3(2)P,600MM,YFH800-	
...3 H001	AA95-03150A	ASSY SUB PCB-F/BOX;FEATURE BOX,S58A,32Z1	
....4 BR01	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4 BR02	AA61-10068A	BRACKET-PCB;M2160,SPTE,T0.3,-,-,-,-	S.N.A
....4 CN01	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4 CN02	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4 CN03	3711-003601	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,ANGLE,	
....4 DC41	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
....4 DC51	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
....4 DX01	2802-001177	RESONATOR-CERAMIC;2.696MHZ,0.4%,BK,10X4.	
....4	AA97-13955A	ASSY SMD;PAL	S.N.A
.....5 0	AA41-00856A	PCB-PFC;CS34A10,DNLE,FR-4,4L,A,1.6T,K55A	S.N.A
.....5 AC01	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC02	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 AC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC04	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 AC05	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC06	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
.....5 AC07	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC08	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC09	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
.....5 AC10	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 AC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC12	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC13	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
.....5 AC14	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC17	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC19	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC20	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC21	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC22	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC23	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC24	2203-001211	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,1608	
.....5 AC25	2203-005342	C-CERAMIC,CHIP;82nF,10%,16V,X7R,TP,1608	
.....5 AC26	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC27	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AC28	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 AL01	3301-001324	CORE-FERRITE BEAD;AB,15OHM,2X1.25X0.9MM,	
.....5 AL02	3301-001324	CORE-FERRITE BEAD;AB,15OHM,2X1.25X0.9MM,	
.....5 AR01	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 AR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 AR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 AR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 AR05	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 AR07	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 AR08	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 AR09	2007-000081	R-CHIP;2.7Kohm,5%,1/16W,DA,TP,1608	
.....5 AR10	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 AR14	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 AR15	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 AR16	2011-000002	R-NETWORK;22ohm,5%,63mW,L,CHIP,8P,TP	
.....5 AR17	2011-000002	R-NETWORK;22ohm,5%,63mW,L,CHIP,8P,TP	
.....5 AR18	2011-000002	R-NETWORK;22ohm,5%,63mW,L,CHIP,8P,TP	
.....5 AR19	2011-000002	R-NETWORK;22ohm,5%,63mW,L,CHIP,8P,TP	
.....5 AR20	2011-000002	R-NETWORK;22ohm,5%,63mW,L,CHIP,8P,TP	
.....5 AR21	2011-000002	R-NETWORK;22ohm,5%,63mW,L,CHIP,8P,TP	
.....5 DC01	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 DC02	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 DC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC04	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 DC05	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC06	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
.....5 DC07	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5 DC08	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 DC09	2402-000170	C-AL,SMD;1uF,20%,50V,GP,TP,4.3x4.3x5.4,	
.....5 DC10	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC12	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 DC13	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 DC14	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	

Loc. No.	Code No.	Description ; Specification	Remark
.....5 DC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC17	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC19	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC20	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 DC21	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC22	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 DC23	2402-000173	C-AL,SMD;4.7uF,20%,35V,GP,TP,4.3x4.3x5.	
.....5 DC24	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 DC25	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC26	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC27	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC28	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC29	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC30	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 DC31	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 DC32	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5 DC33	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 DC34	2203-000888	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,1608	
.....5 DC35	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5 DC36	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 DC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC39	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 DC40	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 DC43	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 DC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC45	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5 DC49	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 DC50	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 DC52	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 DC53	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 DC54	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5 DC55	2203-000491	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,1608	
.....5 DD01	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD02	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD03	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5 DD04	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5 DD05	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5 DD06	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5 DD07	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP	
.....5 DD08	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD09	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD10	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD11	0403-000746	DIODE-ZENER;RLZ3.9B,3.89-4.16V,500MW,LL-	
.....5 DD13	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD14	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD15	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD16	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD17	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD18	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD19	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD20	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
.....5 DD21	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD22	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD23	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DD24	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 DL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 DL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 DL03	2703-001070	INDUCTOR-SMD;100uH,10%,4.5x3.2x3.2mm	
.....5 DQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5 DQ02	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5 DQ03	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5 DQ04	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5 DQ05	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5 DQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5 DQ07	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5 DQ08	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5 DQ09	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
.....5 DQ10	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5 DQ11	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-	
.....5 DR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR05	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR06	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	

Loc. No.	Code No.	Description ; Specification	Remark
.....5 DR07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 DR08	2007-000691	R-CHIP;3.3Mohm,5%,1/16W,DA,TP,1608	
.....5 DR09	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR10	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR13	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5 DR14	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5 DR15	2007-000869	R-CHIP;4.7Kohm,1%,1/16W,DA,TP,1608	
.....5 DR16	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR17	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR18	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR19	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR23	2007-000052	R-CHIP;10Kohm,1%,1/16W,DA,TP,1608	
.....5 DR24	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
.....5 DR25	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....5 DR26	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR27	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
.....5 DR28	2007-000107	R-CHIP;470Kohm,5%,1/16W,DA,TP,1608	
.....5 DR29	2007-000118	R-CHIP;390ohm,5%,1/16W,DA,TP,1608	
.....5 DR30	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR31	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5 DR32	2007-000081	R-CHIP;2.7Kohm,5%,1/16W,DA,TP,1608	
.....5 DR33	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5 DR34	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 DR35	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR36	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR37	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 DR38	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5 DR39	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5 DR40	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....5 DR41	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
.....5 DR42	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR43	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 DR44	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 DR45	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 DR46	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 DR47	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 DR49	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR50	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR51	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR52	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5 DR53	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5 DR54	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5 DR55	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5 DR56	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5 DR57	2007-000211	R-CHIP;1.1Kohm,5%,1/16W,DA,TP,1608	
.....5 DR58	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR59	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR60	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR61	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 DR62	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 DR63	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 DR64	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 DR65	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR66	2007-000088	R-CHIP;7.5Kohm,5%,1/16W,DA,TP,1608	
.....5 DR80	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 DR81	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
.....5 DR82	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
.....5 DR86	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....5 DR87	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....5 DR88	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR90	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 DR91	2007-000259	R-CHIP;1.6Kohm,5%,1/16W,DA,TP,1608	
.....5 DR92	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....5 EC01	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC02	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC04	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC08	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5 EC09	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5 EC10	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5 EC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC12	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC13	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5 EC14	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	

Loc. No.	Code No.	Description ; Specification	Remark
.....5 EC15	2203-000575	C-CERAMIC,CHIP;220NF,10%,25V,X7R,TP,2012	
.....5 EC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC17	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5 EC18	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5 EC19	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5 EC20	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5 EC21	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5 EC22	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5 EC23	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5 EC24	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC26	2203-000783	C-CERAMIC,CHIP;0.33NF,5%,50V,C0G,TP,1608	
.....5 EC29	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5 EC30	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5 EC31	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5 EC32	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC33	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC34	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
.....5 EC35	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,160	
.....5 EC36	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC39	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC40	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC41	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC42	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 EC43	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC44	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 EC45	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC46	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC47	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 EC48	2402-001070	C-AL,SMD;470uF,20%,16V,GP,TP,10x10.2,-	
.....5 EC49	2402-001070	C-AL,SMD;470uF,20%,16V,GP,TP,10x10.2,-	
.....5 EC50	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 EC51	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 EC52	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC53	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC54	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC55	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC59	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 EC60	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 EC62	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5 EC63	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5 EC64	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5 EC65	2203-000681	C-CERAMIC,CHIP;0.027NF,5%,50V,C0G,TP,160	
.....5 EL04	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 EL06	3301-001324	CORE-FERRITE BEAD;AB,15OHM,2X1.25X0.9MM,	
.....5 EL07	3301-001324	CORE-FERRITE BEAD;AB,15OHM,2X1.25X0.9MM,	
.....5 EL08	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 EL09	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 EL13	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 EQ04	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
.....5 EQ05	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.	
.....5 ER02	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ER04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ER06	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5 ER07	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5 ER09	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ER10	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ER12	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....5 ER13	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ER15	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....5 ER16	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ER19	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ER20	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ER21	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ER24	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ER25	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ER26	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ER28	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ER29	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ER30	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ER31	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ER36	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ER38	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ER39	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ER40	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 EX01	2801-004004	CRYSTAL-SMD;20.25MHz,20ppm,28-AAN,13pF,2	

Loc. No.	Code No.	Description ; Specification	Remark
.....5 IC01	1204-001938	IC-DECODER;VSP9407B-B11,MQFP,80P,14X14MM	
.....5 IC02	1204-001814	IC-SELECTOR;CXA2151Q,QFP,48P,144MIL,PLAS	
.....5 IC03	1001-001082	IC-VIDEO SWITCH;BA7657F,-,SOP,24P,300MIL	
.....5 IC04	1204-001989	IC-VIDEO PROCESS;CXA2165Q,QFP,64P,20X14M	
.....5 IC05	1203-002186	IC-POSI.FIXED REG.;18,DPAK,3P,240MIL,PLA	
.....5 IC11	0801-000662	IC-CMOS LOGIC;74HC123,MULTIVIBATOR,SOP,1	
.....5 IC12	1002-001292	IC-A/D CONVERTER;AD9883AKST-110,8BITS,QF	
.....5 IC13	1204-001814	IC-SELECTOR;CXA2151Q,QFP,48P,144MIL,PLAS	
.....5 IC14	1002-001341	IC-D/A CONVERTER;ADV7123KST140,-,LQFP,48	
.....5 IC15	1301-001625	IC-CPLD;M4A3-64/32-7VI,TQFP,48P,-,7.5NS,	
.....5 IC16	1003-001503	IC-DISPLAY DRIVER;SNI,QFP,208P,28X28MM,-	
.....5 IC17	1105-001336	IC-DRAM;4S643232,512Kx32x4Bit,TSOP,86P,4	
.....5 IC18	1105-001336	IC-DRAM;4S643232,512Kx32x4Bit,TSOP,86P,4	
.....5 IC19	1203-001359	IC-POSI.FIXED REG.;1086,TO-263,3P,15.8MM	
.....5 IC20	1203-001211	IC-VOL. DETECTOR;7027,SOT-89,3P,-,PLASTI	
.....5 IC21	1203-002351	IC-VOLTAGE REGULATOR;LF25C,DPAK,3P,240MI	
.....5 IC22	1103-000129	IC-EEPROM;24C02,256x8BIT,SOP,8P,150MIL,1	
.....5 SC01	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 SC02	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 SC03	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 SC04	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 SC05	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 SC06	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 SC10	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 SC11	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 SC12	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 SC13	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 SC14	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 SC15	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC16	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 SC17	2203-005809	C-CERAMIC,CHIP;1000nF,10%,16V,X7R,TP,201	
.....5 SC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC19	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 SC20	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC21	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 SC22	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC23	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 SC24	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 SC25	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 SC26	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 SC27	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 SC28	2203-001656	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,1608	
.....5 SC29	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 SC30	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 SC31	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 SC32	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 SC33	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 SC34	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 SC35	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 SC36	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 SC37	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 SC38	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 SC39	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 SC40	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 SC41	2203-000998	C-CERAMIC,CHIP;0.047NF,5%,50V,C0G,TP,160	
.....5 SC42	2203-000998	C-CERAMIC,CHIP;0.047NF,5%,50V,C0G,TP,160	
.....5 SC43	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 SC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC47	2203-000236	C-CERAMIC,CHIP;0.1NF,5%,50V,C0G,TP,1608	
.....5 SL01	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 SL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 SQ01	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5 SR01	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR02	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR04	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 SR05	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 SR06	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 SR07	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR08	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR09	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 SR10	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 SR11	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 SR12	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR13	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR14	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR26	2007-000052	R-CHIP;10Kohm,1%,1/16W,DA,TP,1608	
.....5 SR27	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....5 SR28	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....5 SR29	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR36	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 SX01	2801-001473	CRYSTAL-SMD;4MHz,50ppm,28-AAN,18pF,150oh	
.....5 XC01	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC02	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC03	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC04	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC05	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC06	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 XC07	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC08	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC09	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC10	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC11	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC12	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC13	2402-001059	C-AL,SMD;220UF,20%,6.3V,-,TP,6X6.6X6.6	
.....5 XC14	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC15	2402-001070	C-AL,SMD;470uF,20%,16V,GP,TP,10x10.2,-	
.....5 XC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC17	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC18	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC19	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC21	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC22	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC23	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC24	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC25	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC26	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC31	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC32	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC33	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC34	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC35	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC36	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC37	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC38	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC39	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC40	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC41	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC42	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC43	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC45	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC46	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC47	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC48	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC49	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC50	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC51	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC52	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC53	2402-001059	C-AL,SMD;220UF,20%,6.3V,-,TP,6X6.6X6.6	
.....5 XC54	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XC55	2402-001059	C-AL,SMD;220UF,20%,6.3V,-,TP,6X6.6X6.6	
.....5 XC56	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 XF03	2901-000226	FILTER-EMI SMD;25V,0.3A,-,100pF,3.2x1.25	
.....5 XL02	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 XL03	2703-001070	INDUCTOR-SMD;100uH,10%,4.5x3.2x3.2mm	
.....5 XL04	2703-001070	INDUCTOR-SMD;100uH,10%,4.5x3.2x3.2mm	
.....5 XR02	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 XR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 XR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 XR05	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 XR06	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 XR07	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ZC01	2402-001059	C-AL,SMD;220UF,20%,6.3V,-,TP,6X6.6X6.6	
.....5 ZC02	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZC03	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 ZC04	2203-005809	C-CERAMIC,CHIP;1000nF,10%,16V,X7R,TP,201	
.....5 ZC05	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZC06	2203-000236	C-CERAMIC,CHIP;0.1NF,5%,50V,C0G,TP,1608	
.....5 ZC07	2402-001059	C-AL,SMD;220UF,20%,6.3V,-,TP,6X6.6X6.6	
.....5 ZC08	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZC09	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 ZC10	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZC11	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	

Loc. No.	Code No.	Description ; Specification	Remark
.....5 ZC12	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZC15	2402-001059	C-AL,SMD;220UF,20%,6.3V,-,TP,6X6.6X6.6	
.....5 ZC16	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZC19	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC20	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC21	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC22	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC23	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC24	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC25	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC26	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC27	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC28	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC29	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC30	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC31	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC32	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC33	2203-002494	C-CERAMIC,CHIP;470nF,10%,16V,X7R,TP,2012	
.....5 ZC41	2402-001070	C-AL,SMD;470uF,20%,16V,GP,TP,10x10.2,-	
.....5 ZC42	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZC43	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZC44	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZC45	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZC46	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZC47	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZC61	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 ZC62	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZC63	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZC64	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 ZD01	0403-000746	DIODE-ZENER;RLZ3.9B,3.89-4.16V,500MW,LL-	
.....5 ZD02	0403-000746	DIODE-ZENER;RLZ3.9B,3.89-4.16V,500MW,LL-	
.....5 ZL01	2703-001070	INDUCTOR-SMD;100uH,10%,4.5x3.2x3.2mm	
.....5 ZL41	2703-001070	INDUCTOR-SMD;100uH,10%,4.5x3.2x3.2mm	
.....5 ZL61	3301-001324	CORE-FERRITE BEAD;AB,15OHM,2X1.25X0.9MM,	
.....5 ZQ01	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23	
.....5 ZR01	2007-000080	R-CHIP;2Kohm,5%,1/16W,DA,TP,1608	
.....5 ZR02	2007-000052	R-CHIP;10Kohm,1%,1/16W,DA,TP,1608	
.....5 ZR03	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR04	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR05	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR06	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR07	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR11	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR12	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR13	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR14	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR15	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR16	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ZR17	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ZR18	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ZR19	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ZR20	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 ZR41	2007-000119	R-CHIP;560ohm,5%,1/16W,DA,TP,1608	
.....5 ZR42	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 ZR43	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ZR44	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 ZR45	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ZR47	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ZR48	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ZR49	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ZR50	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR51	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR52	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR61	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ZR62	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ZR63	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ZR64	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ZR65	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ZR66	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 ZR67	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 ZR68	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 ZR69	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 ZR72	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR73	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 ZR74	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 ZR75	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 ZR76	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	

Loc. No.	Code No.	Description ; Specification	Remark
.....5 ZX01	2801-001473	CRYSTAL-SMD;4MHz,50ppm,28-AAN,18pF,150oh	
....4	AA63-00608A	SHIELD CASE;HERCULES TOP,SPTE,T0.5,W140.	S.N.A
....4	AA63-00685A	SHIELD;STARWARS,SPTE,T0.5,W141.5,H116.0	S.N.A
....4	0202-001167	SOLDER-CREAM;RX3603-2330HO,S45A,PASTE,SN	S.N.A
....4	0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3 H002	AA95-03151A	ASSY SUB PCB-MICOM;MICOM,S58A,PAL,M2-MIC	
....4 CN901	3703-001124	CONNECTOR-BACK PANEL;32P,2R,MALE,ANGLE,A	
....4 CN902	3703-001124	CONNECTOR-BACK PANEL;32P,2R,MALE,ANGLE,A	
....4 IC902	AA97-13974A	ASSY MICOM;,S58A,SDA6001,TM_STWM06_001,0	
.....5 IC902	1102-001126	IC-EPROM;M27V160,2MX8BIT,DIP,42P,570MIL,	
....4 IC904	1203-001140	IC-VOL. DETECTOR;7039,TO-92P,3P,-,PLASTI	
....4 Q901	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
....4 Q902	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
....4 Q905	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
....4 Q906	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
....4 Q907	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
....4 Q908	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	
....4	AA63-00608A	SHIELD CASE;HERCULES TOP,SPTE,T0.5,W140.	S.N.A
....4	AA97-13954A	ASSY SMD;PAL	S.N.A
.....5 0	AA41-00880A	PCB-MICOM;WS32Z10,FR-4,4,A,1.6,T,S58A,2A	S.N.A
.....5 C901	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C902	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C904	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 C905	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5 C907	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C908	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C909	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 C910	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 C911	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 C912	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 C913	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 C914	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 C915	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 C916	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 C917	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 C918	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C919	2203-000815	C-CERAMIC,CHIP;0.033NF,5%,50V,C0G,TP,160	
.....5 C920	2203-000815	C-CERAMIC,CHIP;0.033NF,5%,50V,C0G,TP,160	
.....5 C921	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C922	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C923	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C924	2203-000405	C-CERAMIC,CHIP;0.18NF,5%,50V,C0G,TP,1608	
.....5 C925	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C926	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C927	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C928	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C929	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C930	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C931	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C932	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C933	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 C934	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 C935	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 C936	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 C937	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 C938	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 C939	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 C940	2402-001070	C-AL,SMD;470uF,20%,16V,GP,TP,10x10.2,-	
.....5 C941	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 C942	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 C943	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 C944	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 C945	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 C946	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 C947	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C948	2203-001607	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,1608	
.....5 C949	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
.....5 C950	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 C951	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C952	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C953	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C954	2203-000189	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 C955	2402-000179	C-AL,SMD;47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 C956	2402-001049	C-AL,CHIP;10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....5 C959	2203-000815	C-CERAMIC,CHIP;0.033NF,5%,50V,C0G,TP,160	
.....5 C960	2203-000815	C-CERAMIC,CHIP;0.033NF,5%,50V,C0G,TP,160	
.....5 D901	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	

Loc. No.	Code No.	Description ; Specification	Remark
.....5 D902	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 D903	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 D904	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
.....5 IC901	1204-002105	IC-DECODER;SDA6001-B12,MQFP,128P,28x28mm	
.....5 IC903	1105-001305	IC-DRAM;4S641632,1Mx16x4Bit,TSOP,54P,400	
.....5 IC905	1203-001359	IC-POSI.FIXED REG.;1086,TO-263,3P,15.8MM	
.....5 IC906	1203-002470	IC-POSI.ADJUST REG.;FAN1616AS25X,SOT-223	
.....5 IC907	MD09-00137A	IC MICOM;P-PCFM-012,P-PCFM-012,32,5V,12M	
.....5 L901	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 L902	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L903	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 L904	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 L905	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 L906	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 L907	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 L908	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L909	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L910	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L911	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L912	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L913	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L914	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L915	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L916	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L917	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L918	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L919	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L920	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L921	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L922	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L923	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L924	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L925	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L926	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L927	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L928	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L929	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L930	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L931	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L932	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L933	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L934	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L935	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L936	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 L937	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 Q903	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
.....5 Q904	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
.....5 Q909	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
.....5 R9001	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R9002	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R9003	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R9004	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R9005	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R9007	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R9008	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R9009	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R901	2007-000309	R-CHIP;10ohm,5%,1/16W,DA,TP,1608	
.....5 R9010	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5 R9011	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 R902	2007-000309	R-CHIP;10ohm,5%,1/16W,DA,TP,1608	
.....5 R903	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5 R904	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5 R905	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R906	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R907	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
.....5 R908	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
.....5 R909	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R910	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 R911	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 R912	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R913	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R914	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R915	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R916	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R917	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R918	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R919	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R920	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R921	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R922	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R923	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R924	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R925	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R926	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R927	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 R928	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R929	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R930	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R931	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5 R932	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R933	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R936	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R937	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R938	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R939	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R940	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R943	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R944	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R945	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R946	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R947	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R948	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R949	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R950	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R951	2007-000643	R-CHIP;270ohm,5%,1/16W,DA,TP,1608	
.....5 R952	2007-001002	R-CHIP;510ohm,5%,1/16W,DA,TP,1608	
.....5 R953	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
.....5 R954	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
.....5 R955	2007-000098	R-CHIP;56Kohm,5%,1/16W,DA,TP,1608	
.....5 R956	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R957	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R958	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R959	2007-000098	R-CHIP;56Kohm,5%,1/16W,DA,TP,1608	
.....5 R960	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R961	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R962	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R963	2007-000704	R-CHIP;3.6Kohm,5%,1/16W,DA,TP,1608	
.....5 R964	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R965	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R966	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R967	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R968	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R969	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R970	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R971	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R973	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
.....5 R974	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R975	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R976	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 R977	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R978	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R979	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R980	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R981	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R982	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R983	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 R985	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R986	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R987	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R988	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R989	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R990	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5 R991	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R992	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
.....5 R993	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
.....5 R994	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 R995	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 R996	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 R997	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 R998	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 R999	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 X901	2801-004117	CRYSTAL-SMD;6MHZ,30PPM,28-ABX,20PF,150OH	
.....5 X902	2801-003773	CRYSTAL-SMD;12MHZ,30PPM,28-AAN,20PF,50OH	
....4	AA63-00607A	SHIELD CASE;HERCULES,SPTE,T0.5,W140.0,H8	S.N.A

Loc. No.	Code No.	Description ; Specification	Remark
....4	0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
....4	0202-001167	SOLDER-CREAM;RX3603-2330HO,S45A,PASTE,SN	S.N.A
...3 H003	AA95-03153A	ASSY SUB PCB-DOLBY DIGITAL;DOLBY DIGITAL	
....4 CN02	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4 CN03	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
....4 IC03	AA97-13972A	ASSY MICOM;,S58A,S3P9428XZZ-SOB8,P_SSACM	
.....5	0903-001290	IC-MICROCONTROLLER;S3P9428,8BIT,SOP,32P,	
....4	AA63-00607A	SHIELD CASE;HERCULES,SPTE,T0.5,W140.0,H8	S.N.A
....4	AA63-00608A	SHIELD CASE;HERCULES TOP,SPTE,T0.5,W140.	S.N.A
....4	AA97-13747A	ASSY SMD;WS32Z10HFMXBWT,S58A,PAL	S.N.A
.....5 0	AA41-00900A	PCB SUB;CS32Z10,FR-4,4,00,,180*245,S58A,	S.N.A
.....5 IC01	0801-002518	IC-CMOS LOGIC;74LCX157,2-INPUT MULTIPLEX	
.....5 IC02	0904-001675	IC-DSP;DSP56367,24BIT,LQFP,144P,20X20MM,	
.....5 IC04	0505-001679	FET-SILICON;FDC6301N,N,25V,0.22A,5OHM,0.	
.....5 IC05	1205-002191	IC-CODEC;AK4586VQ,LQFP,44P,10X10MM,PLAST	
.....5 IC06	1201-001907	IC-OP AMP;4580,EMP,TP,8P,5X3.9MM,DUAL,11	
.....5 IC07	1201-001907	IC-OP AMP;4580,EMP,TP,8P,5X3.9MM,DUAL,11	
.....5 IC08	1201-001907	IC-OP AMP;4580,EMP,TP,8P,5X3.9MM,DUAL,11	
.....5 IC09	1204-002017	IC-VOLUME/TONE CONT.;NJW1151M,SDMP,30P,1	
.....5 IC10	1201-001907	IC-OP AMP;4580,EMP,TP,8P,5X3.9MM,DUAL,11	
.....5 IC11	1203-002648	IC-VOLTAGE REGULATOR;BA33B00FP,TO-252,5P	
.....5 IC12	1204-001910	IC-SOUND PROCESSOR;MSP4450G-B8,PLQFP,64P	
.....5 IC13	0801-002769	IC-CMOS LOGIC;MM74HC126,BUFFER,TSSOP,14P	
.....5 MC101	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 MC102	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 MC103	2203-005590	C-CERAMIC,CHIP;330NF,10%,16V,X7R,TP,2012	
.....5 MC105	2203-000715	C-CERAMIC,CHIP;3.3nF,10%,50V,X7R,TP,1608	
.....5 MC107	2203-001554	C-CERAMIC,CHIP;1.8nF,10%,50V,X7R,TP,1608	
.....5 MC108	2203-000715	C-CERAMIC,CHIP;3.3nF,10%,50V,X7R,TP,1608	
.....5 MC109	2402-001158	C-AL,SMD;1UF,20%,50V,WT,TP,4X5.2MM	
.....5 MC110	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 MC111	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 MC112	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 MC113	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 MC114	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 MC115	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 MC116	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 MC117	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 MC118	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 MC119	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 MC120	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 MC121	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 MC122	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 MC123	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 MC124	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 MC125	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 MC126	2402-001140	C-AL,SMD;4.7UF,-,50V,GP,TP,4.3X4.3X5.3MM	
.....5 MC127	2402-001140	C-AL,SMD;4.7UF,-,50V,GP,TP,4.3X4.3X5.3MM	
.....5 MC128	2402-001140	C-AL,SMD;4.7UF,-,50V,GP,TP,4.3X4.3X5.3MM	
.....5 MC129	2402-001140	C-AL,SMD;4.7UF,-,50V,GP,TP,4.3X4.3X5.3MM	
.....5 MC130	2402-001140	C-AL,SMD;4.7UF,-,50V,GP,TP,4.3X4.3X5.3MM	
.....5 MC131	2402-001140	C-AL,SMD;4.7UF,-,50V,GP,TP,4.3X4.3X5.3MM	
.....5 MC132	2402-001140	C-AL,SMD;4.7UF,-,50V,GP,TP,4.3X4.3X5.3MM	
.....5 MC133	2402-001140	C-AL,SMD;4.7UF,-,50V,GP,TP,4.3X4.3X5.3MM	
.....5 MC134	2402-001140	C-AL,SMD;4.7UF,-,50V,GP,TP,4.3X4.3X5.3MM	
.....5 MC135	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 MC136	2402-001140	C-AL,SMD;4.7UF,-,50V,GP,TP,4.3X4.3X5.3MM	
.....5 MC137	2402-001140	C-AL,SMD;4.7UF,-,50V,GP,TP,4.3X4.3X5.3MM	
.....5 MC138	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 MC139	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 MC140	2203-001071	C-CERAMIC,CHIP;0.056NF,5%,50V,C0G,TP,160	
.....5 MC141	2203-001071	C-CERAMIC,CHIP;0.056NF,5%,50V,C0G,TP,160	
.....5 MC143	2203-000552	C-CERAMIC,CHIP;0.02NF,5%,50V,C0G,TP,1608	
.....5 MC144	2203-000552	C-CERAMIC,CHIP;0.02NF,5%,50V,C0G,TP,1608	
.....5 MC146	2402-001158	C-AL,SMD;1UF,20%,50V,WT,TP,4X5.2MM	
.....5 MC149	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 MC150	2203-001554	C-CERAMIC,CHIP;1.8nF,10%,50V,X7R,TP,1608	
.....5 ML101	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 ML102	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 ML103	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 ML104	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 ML105	3301-001082	CORE-FERRITE BEAD;AB,60OHM,3.2X2.5X1.3MM	
.....5 MR101	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 MR102	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 MR103	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 MR104	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 MR105	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 MR110	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 MR111	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
.....5 MR112	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 MR113	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
.....5 MR114	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 MR115	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 MR116	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 MR117	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 MR118	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 MR119	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 MR120	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 MR121	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 MR122	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 MR123	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 MR124	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 MR125	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 MR126	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 MX01	2801-003843	CRYSTAL-SMD;18.432MHz,30ppm,28-AAN,20pF,	
.....5 SC101	2402-001150	C-AL,SMD;47UF,20%,16V,-,TP,6.3X5.8MM	
.....5 SC102	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 SC103	2402-001150	C-AL,SMD;47UF,20%,16V,-,TP,6.3X5.8MM	
.....5 SC104	2402-001150	C-AL,SMD;47UF,20%,16V,-,TP,6.3X5.8MM	
.....5 SC105	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC106	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC107	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC108	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC109	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC110	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 SC111	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC112	2203-000975	C-CERAMIC,CHIP;47nF,10%,25V,X7R,TP,1608,	
.....5 SC113	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC114	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC115	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC116	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC117	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC118	2203-000815	C-CERAMIC,CHIP;0.033NF,5%,50V,C0G,TP,160	
.....5 SC119	2203-000815	C-CERAMIC,CHIP;0.033NF,5%,50V,C0G,TP,160	
.....5 SC120	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC121	2402-001150	C-AL,SMD;47UF,20%,16V,-,TP,6.3X5.8MM	
.....5 SC122	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 SC123	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC124	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 SC125	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC126	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC127	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 SC128	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC129	2402-000130	C-AL,SMD;2.2uF,20%,50V,GP,TP,4.3x4.3x5.	
.....5 SC130	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 SC132	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC133	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC134	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-	
.....5 SC135	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 SC136	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 SC137	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 SC138	2402-001155	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	
.....5 SC139	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 SC140	2203-002398	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,1608	
.....5 SC141	2402-001155	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	
.....5 SC142	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 SC143	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC144	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 SC145	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	
.....5 SC146	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 SC147	2402-001155	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	
.....5 SC148	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 SC149	2402-001155	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	
.....5 SC151	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 SC152	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 SC153	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 SC154	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 SC155	2402-001155	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	
.....5 SC156	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 SC157	2402-001155	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	
.....5 SC159	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 SC160	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....5 SC161	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC162	2402-001042	C-AL,SMD;100uF,20%,16V,GP,TP,6.6x6.6x5.4	

Loc. No.	Code No.	Description ; Specification	Remark
.....5 SC163	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 SC164	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 SC165	2203-005189	C-CERAMIC,CHIP;680nF,+80-20%,16V,Y5V,TP,	
.....5 SC166	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 SC167	2402-001140	C-AL,SMD;4.7UF,-,50V,GP,TP,4.3X4.3X5.3MM	
.....5 SC168	2402-001140	C-AL,SMD;4.7UF,-,50V,GP,TP,4.3X4.3X5.3MM	
.....5 SC169	2203-000552	C-CERAMIC,CHIP;0.02NF,5%,50V,C0G,TP,1608	
.....5 SC170	2203-000552	C-CERAMIC,CHIP;0.02NF,5%,50V,C0G,TP,1608	
.....5 SC171	2402-000176	C-AL,SMD;10uF,20%,16V,GP,TP,4.3x4.3x5.4	
.....5 SC172	2203-005189	C-CERAMIC,CHIP;680nF,+80-20%,16V,Y5V,TP,	
.....5 SC173	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608	
.....5 SC174	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 SC175	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 SC176	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 SC178	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 SC179	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 SC180	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 SC181	2402-001128	C-AL,SMD;100UF,20%,16V,WT,TP,6.3X5.7MM	
.....5 SC182	2402-001150	C-AL,SMD;47UF,20%,16V,-,TP,6.3X5.8MM	
.....5 SC183	2402-001150	C-AL,SMD;47UF,20%,16V,-,TP,6.3X5.8MM	
.....5 SC184	2402-001128	C-AL,SMD;100UF,20%,16V,WT,TP,6.3X5.7MM	
.....5 SC185	2402-001155	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM	
.....5 SC186	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
.....5 SC187	2203-001656	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,1608	
.....5 SC188	2203-000715	C-CERAMIC,CHIP;3.3nF,10%,50V,X7R,TP,1608	
.....5 SC189	2203-000715	C-CERAMIC,CHIP;3.3nF,10%,50V,X7R,TP,1608	
.....5 SC190	2203-000715	C-CERAMIC,CHIP;3.3nF,10%,50V,X7R,TP,1608	
.....5 SC191	2203-000715	C-CERAMIC,CHIP;3.3nF,10%,50V,X7R,TP,1608	
.....5 SC192	2203-000715	C-CERAMIC,CHIP;3.3nF,10%,50V,X7R,TP,1608	
.....5 SC193	2203-000715	C-CERAMIC,CHIP;3.3nF,10%,50V,X7R,TP,1608	
.....5 SC220	2402-000135	C-AL,SMD;22uF,20%,16V,GP,TP,5.3x5.3x5.4	
.....5 SL101	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 SL102	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 SL103	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 SL104	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 SL105	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 SL106	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 SL107	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 SL108	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 SL109	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 SL110	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 SL111	3301-001404	CORE-FERRITE BEAD;AB,30ohm,20x1.25x1mm,2	
.....5 SL112	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm	
.....5 SL113	2703-000274	INDUCTOR-SMD;2.2uH,10%,1.25x2x0.85mm	
.....5 SQ101	0501-002080	TR-SMALL SIGNAL;2SC2412K,NPN,200mW,SC-59	
.....5 SR101	2007-000882	R-CHIP;4.7ohm,5%,1/16W,DA,TP,1608	
.....5 SR102	2007-000098	R-CHIP;56Kohm,5%,1/16W,DA,TP,1608	
.....5 SR103	2007-000805	R-CHIP;36Kohm,5%,1/16W,DA,TP,1608	
.....5 SR104	2007-000122	R-CHIP;1.2Kohm,5%,1/16W,DA,TP,1608	
.....5 SR105	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR106	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR107	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR108	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR109	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 SR110	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR111	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR112	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR113	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR114	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR115	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR116	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR117	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR118	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR119	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR120	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR121	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR122	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR123	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR124	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR125	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR126	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR127	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR128	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR129	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR130	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR131	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR132	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	

Loc. No.	Code No.	Description ; Specification	Remark
.....5 SR133	2007-000458	R-CHIP;18Kohm,5%,1/16W,DA,TP,1608	
.....5 SR137	2007-001167	R-CHIP;75ohm,5%,1/16W,DA,TP,1608	
.....5 SR138	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR139	2007-000077	R-CHIP;470ohm,5%,1/16W,DA,TP,1608	
.....5 SR140	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
.....5 SR141	2007-000134	R-CHIP;33Kohm,5%,1/16W,DA,TP,1608	
.....5 SR142	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5 SR143	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR144	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR145	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5 SR146	2007-000134	R-CHIP;33Kohm,5%,1/16W,DA,TP,1608	
.....5 SR147	2007-000134	R-CHIP;33Kohm,5%,1/16W,DA,TP,1608	
.....5 SR148	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5 SR149	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR150	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR151	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5 SR152	2007-000134	R-CHIP;33Kohm,5%,1/16W,DA,TP,1608	
.....5 SR153	2007-000134	R-CHIP;33Kohm,5%,1/16W,DA,TP,1608	
.....5 SR154	2007-000086	R-CHIP;5.6Kohm,5%,1/16W,DA,TP,1608	
.....5 SR155	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR156	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR157	2007-000083	R-CHIP;3Kohm,5%,1/16W,DA,TP,1608	
.....5 SR158	2007-000134	R-CHIP;33Kohm,5%,1/16W,DA,TP,1608	
.....5 SR159	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR160	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
.....5 SR161	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
.....5 SR162	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
.....5 SR163	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
.....5 SR164	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
.....5 SR165	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
.....5 SR166	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
.....5 SR167	2007-000381	R-CHIP;13Kohm,5%,1/16W,DA,TP,1608	
.....5 SR168	2007-000096	R-CHIP;30Kohm,5%,1/16W,DA,TP,1608	
.....5 SR169	2007-000329	R-CHIP;11Kohm,5%,1/16W,DA,TP,1608	
.....5 SR170	2007-000076	R-CHIP;330ohm,5%,1/16W,DA,TP,1608	
.....5 SR171	2007-000329	R-CHIP;11Kohm,5%,1/16W,DA,TP,1608	
.....5 SR201	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
.....5 SR202	2007-000094	R-CHIP;22Kohm,5%,1/16W,DA,TP,1608	
.....5 SR203	2007-000134	R-CHIP;33Kohm,5%,1/16W,DA,TP,1608	
.....5 SR204	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
.....5 SR205	2007-000134	R-CHIP;33Kohm,5%,1/16W,DA,TP,1608	
.....5 SR501	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
.....5 SX01	2804-001535	OSCILLATOR-CLOCK;12.288MHZ,100PPM,30PF,T	
.....5 SX02	2801-003773	CRYSTAL-SMD;12MHZ,30PPM,28-AAN,20PF,500H	
....4	0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3 IC602	1201-000407	IC-POWER AMP;7050,DIP,8P,-,SINGLE,-,PLAS	
...3 IC603	BP96-00022A	ASSY HEAT SINK P;H/S POWER,MACHINE+NUT,T	S.N.A
...3 IC604	BP96-00022A	ASSY HEAT SINK P;H/S POWER,MACHINE+NUT,T	S.N.A
...3 IC605	BP96-00022A	ASSY HEAT SINK P;H/S POWER,MACHINE+NUT,T	S.N.A
....4 CIS	BP62-00006A	HEAT SINK-PS;AMADEUS,A6063S,T2.0,26,42	S.N.A
....4 CIS	6021-000118	NUT-HEXAGON;1C,M3,ZPC(YEL),SM20C	S.N.A
....4 CIS	6006-001009	SCREW-ASS'Y MACH;WSP,BH,+,M3(WOD6),L12,Z	S.N.A
....4 CIS	1201-001887	IC-AUDIO AMP;TDA7490,FLEXIWATT,25P,29.23	
....4 CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
...3 IC606	BP96-00021A	ASSY HEAT SINK P;H/S POWER,SCREW,TDA7482	S.N.A
....4 CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4 CIS	1201-001888	IC-AUDIO AMP;TDA7482,MULTIWATT,15P,19.6X	
....4 CIS	6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4 CIS	BP62-00006A	HEAT SINK-PS;AMADEUS,A6063S,T2.0,26,42	S.N.A
...3 IC701	1001-001073	IC-VIDEO SWITCH;TEA6415C,VIDEO SWITCH,DI	
...3 IC702	1001-001113	IC-AUDIO SWITCH;TEA6422,SOUND SWITCH ,SD	
...3 IC801	1203-000165	IC-POSI.ADJUST REG.;78R12,TO-220,4P,-,PL	
...3 IC802	1203-000293	IC-POSI.FIXED REG.;7808,TO-220,3P,-,PLAS	
...3 IC803	AA96-50147C	ASSY H/S;-,TR,AA62-30012B,2KA7809A,-	S.N.A
....4	1203-000298	IC-POSI.FIXED REG.;7809,TO-220,3P,-,PLAS	
....4	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	AA62-30012B	HEAT SINK-ES;-,A6063 EXTR,-,-,45(16) T02	S.N.A
...3 IC804	AA96-50397C	ASSY H/S;,AA62-30180J,SI-3050	S.N.A
....4 CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4 CIS	1203-000203	IC-POSI.ADJUST REG.;3050,TO-220,5P,-,PLA	
....4 CIS	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4 CIS	AA62-30180J	HEAT SINK-ES;-,A6063 EXTR,-,WHT,-,-,-,40	S.N.A
...3 IC805	AA96-50397C	ASSY H/S;,AA62-30180J,SI-3050	S.N.A
...3 IC806	1203-001944	IC-POSI.FIXED REG.;78RM33,TO-220,3P,-,PL	
...3 IC807	1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
...3 IC808	1203-000298	IC-POSI.FIXED REG.;7809,TO-220,3P,-,PLAS	
...3 IC905	1103-001274	IC-EEPROM;M24C32,4KX8BIT,PDIP,8P,250MIL,	

Loc. No.	Code No.	Description ; Specification	Remark
...3 ICD601	1204-001775	IC-SOUND PROCESSOR;MSP3410D-C5 9458 ,SDI	
...3 ICD801	1203-001225	IC-POSI.FIXED REG.;78R09,TO-220,4P,-,PLA	
...3 ICD802	1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
...3 ICG01	0801-000314	IC-CMOS LOGIC;74HCT86,OR GATE,DIP,14P,30	
...3 ICS01	1001-001114	IC-VIDEO SWITCH;TEA6425,VIDEO SWITCH ,DI	
...3 ICS02	1001-001113	IC-AUDIO SWITCH;TEA6422,SOUND SWITCH ,SD	
...3 ICS03	1001-000223	IC-VIDEO SWITCH;TEA5114A,-,DIP,16P,334MI	
...3 IF-CAB	AA39-30007A	CBF IF;-,T,100mm,1365#26	
...3 L607	AA27-00277A	COIL CHOKE;30UH,CPTTV,30UH,15%,0.3OHM,5A	
...3 L608	AA27-00276A	COIL CHOKE;60UH,CPTTV,60UH,15%,0.3OHM,3A	
...3 L609	AA27-00277A	COIL CHOKE;30UH,CPTTV,30UH,15%,0.3OHM,5A	
...3 L610	AA27-00277A	COIL CHOKE;30UH,CPTTV,30UH,15%,0.3OHM,5A	
...3 L611	AA27-00277A	COIL CHOKE;30UH,CPTTV,30UH,15%,0.3OHM,5A	
...3 L612	AA27-00277A	COIL CHOKE;30UH,CPTTV,30UH,15%,0.3OHM,5A	
...3 L615	AA27-00277A	COIL CHOKE;30UH,CPTTV,30UH,15%,0.3OHM,5A	
...3 TU01	AA40-00083A	TUNER;TCLS3101PD16A(S),PAL B/G,D/K,I,M,1	
...3 TUP01	AA40-00085A	TUNER;TCPS3000PC16A(S),PAL B/G,D/K,I,M,1	
...3 WIRE01	AA39-20010C	LEAD CONNECTOR-ASSY;,1P,600,YFH800-01,S,	
...3 XD01	2801-004020	CRYSTAL-UNIT;18.432MHz,30ppm,28-AAM,12pF	
...3 Z	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-,	S.N.A
...3	0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3	AA65-00011B	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3	AA65-00011C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3	AA65-30009A	CLAMPER CORE-FBT;-,ABS,V0,-,BLK,-	S.N.A
...3	AA65-30104B	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3	AA97-13752A	ASSY AUTO-MAIN;WS32Z10HFMXBWT,S58A,CIS	S.N.A
....4 0	AA41-00883A	PCB MAIN;WS32Z10,FR-4,2L,A,1.6,T,S38A,1,	S.N.A
....4 C101	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4 C102	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4 C103	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4 C104	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4 C105	2201-000611	C-CERAMIC,DISC;0.056NF,5%,50V,C0G,TP,7X3	
....4 C106	2201-000611	C-CERAMIC,DISC;0.056NF,5%,50V,C0G,TP,7X3	
....4 C107	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4 C108	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C109	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4 C110	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C201	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
....4 C204	2401-002459	C-AL;220uF,20%,25V,LZ,TP,10x16,5	
....4 C205	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C206	2201-000411	C-CERAMIC,DISC;0.27NF,10%,50V,Y5P,TP,4X3	
....4 C601	2401-000703	C-AL;2200uF,20%,25V,GP,-,12.5x25mm,	
....4 C602	2401-000703	C-AL;2200uF,20%,25V,GP,-,12.5x25mm,	
....4 C605	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4 C606	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4 C607	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4 C608	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4 C609	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C610	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C611	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C612	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C614	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C615	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C617	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C618	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C619	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C620	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C621	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C622	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C624	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4 C625	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4 C626	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4 C627	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4 C628	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4 C630	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4 C631	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4 C632	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4 C633	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4 C634	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4 C636	2202-000210	C-CERAMIC,MLC-AXIAL;270pF,10%,50V,Y5P,TP	
....4 C637	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,	
....4 C638	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4 C639	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C640	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4 C641	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C642	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4 C643	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	

Loc. No.	Code No.	Description ; Specification	Remark
....4 C644	2202-000216	C-CERAMIC,MLC-AXIAL;0.027NF,5%,50V,SL,TP	
....4 C645	2202-000216	C-CERAMIC,MLC-AXIAL;0.027NF,5%,50V,SL,TP	
....4 C647	2202-000863	C-CERAMIC,MLC-AXIAL;560pF,10%,50V,Y5P,TP	
....4 C648	2202-000863	C-CERAMIC,MLC-AXIAL;560pF,10%,50V,Y5P,TP	
....4 C649	2202-000863	C-CERAMIC,MLC-AXIAL;560pF,10%,50V,Y5P,TP	
....4 C650	2202-000863	C-CERAMIC,MLC-AXIAL;560pF,10%,50V,Y5P,TP	
....4 C651	2202-000863	C-CERAMIC,MLC-AXIAL;560pF,10%,50V,Y5P,TP	
....4 C653	2301-000445	C-FILM,PEF;4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
....4 C654	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
....4 C655	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
....4 C659	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4 C660	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,	
....4 C661	2301-000247	C-FILM,PEF;33nF,5%,50V,TP,8.1x4.5x13mm,5	
....4 C662	2301-000247	C-FILM,PEF;33nF,5%,50V,TP,8.1x4.5x13mm,5	
....4 C663	2301-000247	C-FILM,PEF;33nF,5%,50V,TP,8.1x4.5x13mm,5	
....4 C664	2301-000247	C-FILM,PEF;33nF,5%,50V,TP,8.1x4.5x13mm,5	
....4 C665	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
....4 C666	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
....4 C667	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
....4 C668	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
....4 C669	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
....4 C670	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
....4 C671	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
....4 C672	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4 C673	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4 C674	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4 C675	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4 C676	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4 C677	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4 C678	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4 C679	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4 C681	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4 C682	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4 C683	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4 C684	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4 C685	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4 C686	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
....4 C687	2401-000620	C-AL;2.2uF,10%,50V,GP,TP,5x11,5	
....4 C688	2401-000620	C-AL;2.2uF,10%,50V,GP,TP,5x11,5	
....4 C689	2401-000620	C-AL;2.2uF,10%,50V,GP,TP,5x11,5	
....4 C690	2401-000620	C-AL;2.2uF,10%,50V,GP,TP,5x11,5	
....4 C691	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4 C692	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4 C693	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4 C694	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4 C695	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C696	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C697	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C698	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C701	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C702	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C703	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C704	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C705	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C706	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C707	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C708	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C709	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C710	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C711	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C712	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C713	2401-001363	C-AL;470uF,20%,16V,GP,TP,10x12.5,5	
....4 C714	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C715	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4 C716	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 C717	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 C718	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 C719	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 C720	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 C721	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 C722	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 C723	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 C725	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C726	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C727	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C729	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C730	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	

Loc. No.	Code No.	Description ; Specification	Remark
....4 C731	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C732	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C733	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C734	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4 C735	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4 C736	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C740	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C741	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 C742	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4 C743	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4 C744	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4 C745	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4 C746	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C748	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 C801	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4 C802	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C803	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4 C804	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C805	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4 C806	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C807	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4 C808	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C809	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4 C810	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C811	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4 C812	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C813	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4 C814	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C815	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4 C816	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C819	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4 C820	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C821	2401-002594	C-AL;220uF,20%,16V,GP,TP,8x11.5,5	
....4 C822	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C823	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C824	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4 C825	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4 C826	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C827	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4 C828	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C901	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4 C902	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C903	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 C906	2401-003473	C-AL;680UF,20%,16V,GP,TP,10X12.5MM,5	
....4 CD01	2401-003561	C-AL;1uF,10%,50V,GP,TP,5x11mm,5	
....4 CD02	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 CD03	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
....4 CD04	2401-001989	C-AL;4.7uF,20%,50V,BP,TP,5x11,5	
....4 CD05	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CD06	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CD07	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4 CD08	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4 CD09	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 CD10	2401-001026	C-AL;3.3UF,20%,50V,GP,TP,5X11,5	
....4 CD11	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CD12	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 CD13	2201-000558	C-CERAMIC,DISC;0.47NF,10%,50V,Y5P,TP,5X3	
....4 CD14	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4 CD15	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
....4 CD16	2202-000286	C-CERAMIC,MLC-AXIAL;56pF,5%,50V,SL,TP,1.	
....4 CD17	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
....4 CD18	2201-000304	C-CERAMIC,DISC;0.001NF,0.25PF,50V,C0G,TP	
....4 CD19	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 CD20	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4 CD21	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4 CD22	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 CG01	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CG02	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CG03	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4 CG04	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 CG05	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CN703A	3711-002648	CONNECTOR-HEADER;BOX,9P,1R,2.5mm,STRAIGH	
....4 CN704A	3711-002647	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH	
....4 CN903A	3711-002645	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH	
....4 CN904A	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
....4 CNG01A	3711-002646	CONNECTOR-HEADER;BOX,7P,1R,2.5mm,STRAIGH	
....4 CNT01	3711-002646	CONNECTOR-HEADER;BOX,7P,1R,2.5mm,STRAIGH	

Loc. No.	Code No.	Description ; Specification	Remark
....4 CP03	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4 CP04	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4 CP07	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
....4 CP08	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 CS01	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS02	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS03	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS04	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS05	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS06	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS07	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS08	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS09	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS10	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS12	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS13	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS14	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS15	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS17	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 CS18	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 CS19	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 CS20	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 CS23	2305-001037	C-FILM,MPEF;330nF,5%,63V,TP,7.5x5.5x14.5	
....4 CS24	2305-001037	C-FILM,MPEF;330nF,5%,63V,TP,7.5x5.5x14.5	
....4 CS25	2305-001037	C-FILM,MPEF;330nF,5%,63V,TP,7.5x5.5x14.5	
....4 CS26	2305-001037	C-FILM,MPEF;330nF,5%,63V,TP,7.5x5.5x14.5	
....4 CS27	2305-001037	C-FILM,MPEF;330nF,5%,63V,TP,7.5x5.5x14.5	
....4 CS28	2305-001037	C-FILM,MPEF;330nF,5%,63V,TP,7.5x5.5x14.5	
....4 CS29	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
....4 CS30	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4 CS32	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4 CS33	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4 CS34	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4 CS35	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4 CW01	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 CW02	2301-000247	C-FILM,PEF;33nF,5%,50V,TP,8.1x4.5x13mm,5	
....4 CW03	2202-000216	C-CERAMIC,MLC-AXIAL;0.027NF,5%,50V,SL,TP	
....4 CW04	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
....4 CW05	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
....4 CW06	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3	
....4 CW07	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
....4 CW08	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4 CW09	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4 CW10	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
....4 CW11	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4 CW12	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
....4 CW13	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
....4 CW14	2301-000247	C-FILM,PEF;33nF,5%,50V,TP,8.1x4.5x13mm,5	
....4 CW15	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 CW16	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
....4 CW17	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4 CW18	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
....4 CW19	2305-000411	C-FILM,MPEF;470nF,5%,50V,TP,7.3x4.8x5.5m	
....4 CW20	2202-000863	C-CERAMIC,MLC-AXIAL;560pF,10%,50V,Y5P,TP	
....4 CW21	2202-000863	C-CERAMIC,MLC-AXIAL;560pF,10%,50V,Y5P,TP	
....4 D601	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4 D602	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4 D603	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4 D604	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4 D605	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4 D606	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4 D801	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
....4 DDZ01	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4 DDZ02	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4 DDZ03	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4 DG01	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
....4 DZ101	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4 DZ601	0403-001316	DIODE-ZENER;MTZJ3.0A,2.85-3.07V,500mW,DO	
....4 DZ602	0403-000367	DIODE-ZENER;UZ7.5BSC,7.5V,7.33-7.64V,500	
....4 DZ603	0403-000367	DIODE-ZENER;UZ7.5BSC,7.5V,7.33-7.64V,500	
....4 DZ604	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
....4 DZ605	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4 DZ606	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
....4 DZ901	0403-000714	DIODE-ZENER;MTZJ3.3B,3.3V,3.32-3.53V,500	
....4 GT101	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT801	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 L101	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	

Loc. No.	Code No.	Description ; Specification	Remark
....4 L102	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 L103	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 L104	2701-000116	INDUCTOR-AXIAL;10uH,10%,4.2x9.8mm	
....4 L106	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4 L601	2701-001027	INDUCTOR-AXIAL;1uH,10%,4.5x14mm	
....4 L602	2701-001027	INDUCTOR-AXIAL;1uH,10%,4.5x14mm	
....4 L603	2701-001027	INDUCTOR-AXIAL;1uH,10%,4.5x14mm	
....4 L604	2701-001027	INDUCTOR-AXIAL;1uH,10%,4.5x14mm	
....4 L605	2701-001027	INDUCTOR-AXIAL;1uH,10%,4.5x14mm	
....4 L606	2701-001027	INDUCTOR-AXIAL;1uH,10%,4.5x14mm	
....4 L613	2701-001027	INDUCTOR-AXIAL;1uH,10%,4.5x14mm	
....4 L614	2701-001027	INDUCTOR-AXIAL;1uH,10%,4.5x14mm	
....4 L616	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4 L617	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4 L618	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4 L619	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4 L620	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4 L621	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4 L622	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4 L623	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4 L701	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4 L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 L703	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 L704	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 L705	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 L706	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 L707	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 L709	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 L710	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 L713	2701-000184	INDUCTOR-AXIAL;4.7uH,10%,2.5x3.4mm	
....4 L714	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 L715	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 L801	2701-001040	INDUCTOR-AXIAL;10uH,10%,4.5x14mm	
....4 L802	2701-001040	INDUCTOR-AXIAL;10uH,10%,4.5x14mm	
....4 L803	2701-000112	INDUCTOR-AXIAL;100uH,10%,3x7mm	
....4 L805	2701-001040	INDUCTOR-AXIAL;10uH,10%,4.5x14mm	
....4 L902	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 LD01	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 LD02	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 LD03	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 LD04	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 LD05	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4 LD06	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 LG01	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4 LP02	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 LP03	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 LP04	2701-000116	INDUCTOR-AXIAL;10uH,10%,4.2x9.8mm	
....4 LP06	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4 LS01	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 LS02	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 LS03	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 LS04	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 LS07	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4 LS08	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
....4 Q601	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q602	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q603	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q701	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,T	
....4 Q702	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q703	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q704	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q705	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q706	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q707	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q708	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4 Q709	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q710	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q711	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q712	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,T	
....4 Q713	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q801	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q802	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q901	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,T	
....4 Q902	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,T	
....4 QG01	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 QG02	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 QG03	0504-000123	TR-DIGITAL;KSR1010,NPN,300mW,10K,TO-92,T	
....4 QS02	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 QS03	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 R101	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R102	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R110	2003-001093	R-METAL OXIDE(S);12Kohm,5%,2W,AF,TP,3.9x	
....4 R202	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R203	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R204	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R205	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R206	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R209	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R210	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R211	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R215	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R225	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R226	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R227	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R601	2004-002022	R-METAL(S);51Kohm,1%,1/2W,AA,TP,2.4x6.4m	
....4 R602	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R603	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R604	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R605	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R606	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R607	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R608	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R609	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R610	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R611	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R612	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R613	2001-001146	R-CARBON(S);4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R614	2001-001187	R-CARBON(S);75OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 R615	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R616	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R617	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R618	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R619	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 R620	2001-001077	R-CARBON(S);150OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R621	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R622	2001-001170	R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R623	2004-002022	R-METAL(S);51Kohm,1%,1/2W,AA,TP,2.4x6.4m	
....4 R624	2004-002022	R-METAL(S);51Kohm,1%,1/2W,AA,TP,2.4x6.4m	
....4 R625	2004-002022	R-METAL(S);51Kohm,1%,1/2W,AA,TP,2.4x6.4m	
....4 R626	2004-002022	R-METAL(S);51Kohm,1%,1/2W,AA,TP,2.4x6.4m	
....4 R627	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R628	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R629	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R630	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R631	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R632	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R633	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R634	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R635	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R636	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R637	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R638	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R639	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R640	2001-000337	R-CARBON;130KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R641	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R642	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R643	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R644	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R645	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R646	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R647	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R648	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R649	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R650	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R651	2001-000908	R-CARBON;62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R652	2001-000337	R-CARBON;130KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R653	2001-000337	R-CARBON;130KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R654	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R655	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R656	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R657	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R658	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R659	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R660	2001-000908	R-CARBON;62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Loc. No.	Code No.	Description ; Specification	Remark
....4 R661	2001-000908	R-CARBON;62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R662	2001-000908	R-CARBON;62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R663	2001-000908	R-CARBON;62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R664	2001-000908	R-CARBON;62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R665	2001-000908	R-CARBON;62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R666	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R667	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R668	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R669	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R670	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R671	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R672	2001-000908	R-CARBON;62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R673	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R674	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R675	2004-002022	R-METAL(S);51Kohm,1%,1/2W,AA,TP,2.4x6.4m	
....4 R676	2001-001179	R-CARBON(S);68KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R677	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 R678	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R679	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R680	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R681	2001-000908	R-CARBON;62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R682	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R683	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R701	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R702	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R703	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R704	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R705	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R706	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R707	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R708	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R709	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R710	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R712	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R713	2001-000761	R-CARBON;430OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R714	2001-000761	R-CARBON;430OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R715	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R716	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R717	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R718	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R719	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R720	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R721	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R722	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R724	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R727	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R728	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R729	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R730	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R731	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R732	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R733	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R734	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R735	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4 R736	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4 R737	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R738	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R739	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R740	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R741	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R742	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R743	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R744	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R745	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R746	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R748	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R749	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R750	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R751	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R752	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R753	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R754	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R755	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R756	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R758	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R759	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R761	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R762	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R763	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R764	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
....4 R765	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R766	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R767	2001-001102	R-CARBON(S);200OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R768	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R769	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R770	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R771	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R801	2009-000026	R-METAL PLATE;0.15OHM,10%,5W,CL,TP,5X14X	
....4 R802	2009-000026	R-METAL PLATE;0.15OHM,10%,5W,CL,TP,5X14X	
....4 R803	2009-000026	R-METAL PLATE;0.15OHM,10%,5W,CL,TP,5X14X	
....4 R804	2001-000908	R-CARBON;62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R901	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R902	2008-001022	R-FUSIBLE(S);10ohm,5%,1W,AF,TP,2.5x6.5mm	
....4 R906	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R907	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R908	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R909	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RC103	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RD01	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RD02	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RD03	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RD04	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RD07	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RD08	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RD09	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RD10	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RG01	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RG02	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RG03	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RG04	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RG05	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RG06	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RG08	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS01	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4 RS02	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4 RS03	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4 RS04	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
....4 RS07	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS08	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS09	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS10	2001-001006	R-CARBON;82OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS11	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS12	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS13	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS14	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS15	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS16	2001-001035	R-CARBON;91OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS19	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS20	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS21	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS22	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS23	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS24	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS26	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS27	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS28	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS29	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS30	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS31	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RT01	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RT02	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RT03	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RT04	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RT05	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
..2	AA94-12594A	ASSY PCB POWER;,S58A,32Z10,CIS	
...3 C407	2303-000186	C-FILM,PPF;22nF,5%,400V,BK,19.5x13.5x8,1	
...3 C408	2306-000324	C-FILM,MPPF;3.3nf,5%,1.6KV,TP,28.5x13.5x	
...3 C409	2306-000195	C-FILM,MPPF;360nF,5%,400V,TP,26x19x11.5,	
...3 C412	2301-001539	C-FILM,MPPF;1000NF,5%,400V,BK,28*25*18,2	
...3 C413	2306-000324	C-FILM,MPPF;3.3nf,5%,1.6KV,TP,28.5x13.5x	
...3 C419	2306-001021	C-FILM,MPPF;100nF,5%,630V,TP,26x8.5x16.5	
...3 C427	2306-000326	C-FILM,MPPF;4.7nF,5%,1.6KV,TP,28.5x16x9m	
...3 C809	2306-000323	C-FILM,MPPF;2.2nF,5%,1.6KV,TP,28.5x15.5x	
...3 C813	2401-003370	C-AL;47uF,20%,450V,GP,BK,16X35.5,7.	

Loc. No.	Code No.	Description ; Specification	Remark
...3 C814	2401-003465	C-AL;680UF,20%,450V,GP,BK,35X60MM,22.5	
...3 C819	2401-002287	C-AL;470uF,20%,200V,WT,BK,25x40,10	
...3 C820	2401-003024	C-AL;220uF,20%,200V,WT,TP,22x35,10	
...3 CH04	2301-001041	C-FILM,PPF;15nF,5%,1.6KV,TP,29x14x21.5,2	
...3 CH05	2301-001041	C-FILM,PPF;15nF,5%,1.6KV,TP,29x14x21.5,2	
...3 CN801	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
...3 CN803	3710-001103	CONNECTOR-SOCKET;14P,1R,2.5mm,STRAIGHT,S	
...3 CN804	3710-001103	CONNECTOR-SOCKET;14P,1R,2.5mm,STRAIGHT,S	
⚠ ...3 CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ ...3 CX802S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ ...3 CX803S	2306-000112	C-FILM,MPPF;100nF,20%,250V,BK,-,15mm	
⚠ ...3 CY801S	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
⚠ ...3 D804	0402-000250	DIODE-RECTIFIER;RG4C,1000V,1A,-	
⚠ ...3 D806	AA96-50310A	ASSY H/S;-,POWER,AA62-30150C,RBV606,-	S.N.A
....4	AA62-30150C	HEAT SINK-ES;-,A6063 EXTR,-,WHT,40(24.5)	S.N.A
....4	AA60-30003A	WASHER;T1.5,SBHG-1	S.N.A
....4	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	0402-000549	DIODE-BRIDGE;RBV606,600V,6A,-,BK	
....4	0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
⚠ ...3 D814	AA96-00111C	ASSY H/S;-,-,AA62-30013L,FML-G12S,-	S.N.A
....4	0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
....4	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	AA62-30013L	HEAT SINK-ES;-,-,-,-,44/22,-,WHT,-,-,-,-	S.N.A
⚠ ...3 D817	AA96-00309B	ASSY H/S;-,POWER,AA62-00061A,FMG-G2CS(1)	S.N.A
....4	AA62-00061A	HEAT SINK-PS;-,-,T1.0,SILVER,-,-,-,-,104	S.N.A
....4	6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4	0402-001230	DIODE-RECTIFIER;FMG-G2CS,1000V,3A,TO-220	
....4	0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
....4	0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
⚠ ...3 D819	0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
...3 DZ801	0406-001007	DIODE-TVS;P6KE180A,171/180/189V,600W,CAS	
⚠ ...3 FP801S	3601-001007	FUSE-CARTRIDGE;250V,6.3A,TIME-LAG,GLASS,	
...3 GT301	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5-,NYLON66	S.N.A
...3 IC301	AA96-50381A	ASSY H/S;-,-,AA62-30180B,LA7845,-	S.N.A
....4	0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4	1204-000517	IC-VERTICAL DEF.;LA7845,SIP,7P,-,PLASTIC	
....4	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	AA62-30180B	HEAT SINK-ES;-,A6063 EXTR.,2,WHT,70MM,-,	S.N.A
⚠ ...3 IC403	1202-000103	IC-VOLTAGE COMP.;393,DIP,8P,300MIL,DUAL,	
⚠ ...3 IC801S	AA96-50364B	ASSY H/S;-,3300UF,+-20%,13*21,1,AA62-301	S.N.A
....4 CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
....4 CIS	1203-002091	IC-PWM CONTROLLER;6658,TO-220,5P,-,PLAST	
....4 CIS	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4 CIS	AA62-30181A	HEAT SINK-ES;A6063,EXTR,SILVER,WHT,ANOD,	S.N.A
⚠ ...3 IC803S	1203-002177	IC-PWM CONTROLLER;VIPER12ADIP,DIP,8P,300	
...3 ICH01	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV	
...3 JP801	AA39-00047D	LEAD CONNECTOR-ASSY;,1P,150MM,JUMPER,BLK	
⚠ ...3 L401	AA27-40003J	COIL HORIZ. WIDTH;-,3mH,ER14 20,PI0.35,S	
...3 L402	AA27-10004F	COIL CHOKE;-,56uH,K,-,2.5A,BK,-,DR12x15,	
⚠ ...3 L403	AA27-00150A	COIL HORIZ. WIDTH;,1.2MH,BK	
...3 L404	AA27-00015A	COIL LINEARITY;-,7.3UH,L81 DR15X18,-,-,B	
...3 L405	AA27-40003P	COIL HORIZ. WIDTH;-,120uH/180uH,Th8x20,U	
...3 L812	AA27-10002L	COIL CHOKE;-,24uH,K,-,2A,-,24UH-K,10x10m	
...3 L815	AA27-10002L	COIL CHOKE;-,24uH,K,-,2A,-,24UH-K,10x10m	
...3 L819	AA27-10002L	COIL CHOKE;-,24uH,K,-,2A,-,24UH-K,10x10m	
...3 LS401	AA27-10002V	COIL CHOKE;-,6.3mH,K,-,500mA,-,NY632K(50	
⚠ ...3 LX801S	AA29-30001Z	FILTER LINE NOISE;-,10mH,2.8A,-,SQE3535	
⚠ ...3 LX802S	AA29-30002D	FILTER LINE NOISE;-,10mH,2.8A,-,SQE-3535	
⚠ ...3 NT801S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ ...3 PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
⚠ ...3 PT801S	1404-001154	THERMISTOR-PTC;4.5OHM,+30%/-20%,220V,270	
...3 Q403	0505-001723	FET-SILICON;FQP630TSTU,N,200V,9A,0.4OHM,	
...3 Q404	0505-001116	FET-SILICON;BUZ73A,N,200V,22A,0.6ohm,40W	
...3 Q405	AA96-00310B	ASSY H/S;AA62-00062A,SCREW,FJL6920,FMP-3	S.N.A
....4 CIS	AA62-00062A	HEAT SINK-PS;-,-,T2.0,SILVER,-,-,-,-,108	S.N.A
....4 CIS	AA60-30001A	WASHER-PLATE;M3,ID3.5,15X8.5,T1.0,SBHG	S.N.A
....4 CIS	AA02-00007A	SUB ETC-MICA;,MICA,22X30X0.1MM	S.N.A
....4 CIS	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4 CIS	0502-001230	TR-POWER;FJL6920YDTU,N,200000MW,TO-264 F	
....4 CIS	0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	
....4 CIS	0205-001027	OIL-SILICON;G746,-,-	S.N.A
...3 Q801	1004-000101	IC-ECC;SE-140N,DIP,-,-,ST,-,PLASTIC,1	
...3 QH04	0502-000442	TR-POWER;2SC4636RB,NPN,2W,TO-220,ST,10-	
...3 R815	2003-002206	R-METAL OXIDE(S);27Kohm,5%,3W,AG,TP,6x16	
...3 R816	2003-002206	R-METAL OXIDE(S);27Kohm,5%,3W,AG,TP,6x16	
⚠ ...3 RL801S	3501-001040	RELAY-POWER;12VDC,500MW,10000MA,1FORMA,1	
⚠ ...3 RL802S	3501-001053	RELAY-POWER;5VDC,530MW,10000MA,1FORMA,15	

Loc. No.	Code No.	Description ; Specification	Remark
...3 SWS01	3409-000138	SWITCH-LEVER;30V,200mA,SP3T,NON SHORTING	
...3 SWS02	3409-000138	SWITCH-LEVER;30V,200mA,SP3T,NON SHORTING	
...3 T401	AA26-50001S	TRANS-HORIZ.DRIVE;-,-,-,6.0mH,-,-,44uH,-	
...3 T402	AA26-90002C	TRANS-DUMMY;-,-,-,-,-,-,-,-,-,-,-,-,EER2	
⚠ ...3 T444S	AA26-00085A	TRANS FBT;FUJ-32C001F(S),W32,1.95mH,-,-,	
⚠ ...3 T801S	AA26-00186A	TRANS SWITCHING;EER5345,S57A.WS32Z4HF9X,	
⚠ ...3 TS801S	BP26-00011A	TRANS SWITCHING-(DPMS);EI1916,J54A,90 ~2	
...3	0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3	AA97-07503N	ASSY AUTO-POWER;,S58A	S.N.A
....4 0	AA41-00874A	PCB-POWER;WS32Z10,CEM-1,1,A,1.6,T,S58A,1	S.N.A
....4 C301	2301-000160	C-FILM,PEF;12nF,5%,50V,TP,11.0x6.0x9.0mm	
....4 C302	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
....4 C304	2401-000365	C-AL;100uF,20%,50V,WT,TP,10x12.5mm,	
....4 C305	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
....4 C306	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
....4 C307	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
....4 C401	2301-000247	C-FILM,PEF;33nF,5%,50V,TP,8.1x4.5x13mm,5	
....4 C402	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5	
....4 C406	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
....4 C410	2301-000188	C-FILM,PEF;1nF,5%,100V,TP,10.5x12.5x6.5,	
....4 C411	2301-001143	C-FILM,PPF;56nF,5%,400V,TP,20x10x17,7.5	
....4 C416	2401-001527	C-AL;47uF,20%,250V,HR,TP,13x25mm,5m	
....4 C417	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
....4 C418	2201-000291	C-CERAMIC,DISC;1NF,10%,500V,Y5P,TP,7.5X3	
....4 C420	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4 C421	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4 C422	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4 C423	2401-001655	C-AL;680uF,20%,25V,GP,TP,10x20,5	
....4 C424	2401-002597	C-AL;220uF,20%,35V,GP,TP,10x12.5,5	
....4 C425	2305-000178	C-FILM,MPEF;10nF,5%,100V,TP,-,5mm	
....4 C426	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
....4 C428	2301-000111	C-FILM,PEF;1.8nF,5%,50V,TP,6.5x3.0x5.5mm	
....4 C429	2305-000196	C-FILM,MPEF;150nF,5%,63V,TP,-,5mm	
....4 C430	2401-001655	C-AL;680uF,20%,25V,GP,TP,10x20,5	
....4 C431	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4 C440	2201-000291	C-CERAMIC,DISC;1NF,10%,500V,Y5P,TP,7.5X3	
....4 C452	2305-000178	C-FILM,MPEF;10nF,5%,100V,TP,-,5mm	
....4 C453	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
....4 C454	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4 C803	2201-000315	C-CERAMIC,DISC;2.2NF,+80-20%,250V,Y5U,TP	
....4 C804	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
....4 C805	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
....4 C806	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
....4 C808	2201-000558	C-CERAMIC,DISC;0.47NF,10%,50V,Y5P,TP,5X3	
....4 C810	2401-000569	C-AL;1uF,20%,250V,GP,TP,6.3x11,5	
....4 C811	2201-000315	C-CERAMIC,DISC;2.2NF,+80-20%,250V,Y5U,TP	
....4 C812	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
....4 C816	2201-002041	C-CERAMIC,DISC;0.82NF,10%,2KV,Y5P,TP,9X5	
....4 C817	2301-001171	C-FILM,PPF;10nF,5%,400V,TP,20x6.5x13,7.5	
....4 C818	2201-000551	C-CERAMIC,DISC;0.47NF,10%,1KV,Y5P,TP,6.3	
....4 C821	2201-000551	C-CERAMIC,DISC;0.47NF,10%,1KV,Y5P,TP,6.3	
....4 C822	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
....4 C824	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4 C825	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
....4 C826	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
....4 C828	2401-001054	C-AL;3300uF,20%,25V,GP,TP,18x25,7.5	
....4 C829	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
....4 C833	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
....4 C834	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
....4 C835	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4 C836	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
....4 C838	2401-003473	C-AL;680UF,20%,16V,GP,TP,10X12.5MM,5	
....4 C839	2201-000551	C-CERAMIC,DISC;0.47NF,10%,1KV,Y5P,TP,6.3	
....4 C841	2401-000722	C-AL;2200uF,20%,25V,WT,TP,16x25,7.5	
....4 C899	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm	
....4 CH01	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
....4 CH02	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4 CH06	2401-000038	C-AL;470uF,20%,25V,GP,TP,10x12.5mm,	
....4 CH07	2401-000287	C-AL;100uF,20%,16V,WT,TP,6.3x11,5	
....4 CH08	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
....4 CH11	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
....4 CN805	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGH	
....4 CS01	2301-001268	C-FILM,PPF;33nF,5%,630V,TP,20x11x17,7.5	
....4 D301	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4 D401	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4 D402	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4 D403	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,	

Loc. No.	Code No.	Description ; Specification	Remark
⚠ 4 D404	0402-000493	DIODE-RECTIFIER;1R5GU41,400V,1.5A,DO-15L	
⚠ 4 D405	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 4 D406	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	
⚠ 4 D408	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 4 D409	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
⚠ 4 D410	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4 D411	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4 D412	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4 D450	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4 D451	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4 D801	0402-000532	DIODE-RECTIFIER;ERC13-08,800V,1.2A,DO-20	
⚠ 4 D802	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4 D803	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4 D805	0402-000532	DIODE-RECTIFIER;ERC13-08,800V,1.2A,DO-20	
⚠ 4 D807	0402-001111	DIODE-RECTIFIER;1N5397GP,600V,1.5A,DO-20	
⚠ 4 D808	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
⚠ 4 D809	0401-000006	DIODE-SWITCHING;BAV21,250V,250mA,DO-35,T	
⚠ 4 D810	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
⚠ 4 D811	1405-001030	VARISTOR;120V,2500A,14x8.5mm,TP	
⚠ 4 D813	0404-001056	DIODE-SCHOTTKY;RK16,60V,1.5A,DO-204AC,TP	
⚠ 4 D816	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4 D820	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4 D821	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4 D823	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
....4 DH01	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
....4 DH02	0402-000254	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	
....4 DS01	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4 DS02	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
....4 DZ301	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4 DZ302	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
....4 DZ303	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
....4 DZ304	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
....4 DZ305	0403-001325	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	
....4 DZ306	0403-000716	DIODE-ZENER;MTZJ4.7B,4.7V,4.55-4.8V,500m	
....4 DZ307	0403-001330	DIODE-ZENER;MTZJ30A,26.99-28.39V,500mW,D	
....4 DZ401	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
....4 DZ402	0403-001325	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	
....4 DZ410	0403-001316	DIODE-ZENER;MTZJ3.0A,2.85-3.07V,500mW,DO	
....4 DZ802	0403-001328	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	
....4 DZ803	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
....4 EL401	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL402	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL403	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL404	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL405	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL406	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL407	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL408	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL801	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL802	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL803	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL804	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL805	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL806	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL807	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL808	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EL810	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EL811	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4 EY301	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY302	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY303	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY304	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY401	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY402	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY403	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY404	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY405	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY406	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY407	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY408	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY409	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY410	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY411	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY412	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY413	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY414	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY415	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A

Loc. No.	Code No.	Description ; Specification	Remark
....4 EY416	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY417	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY419	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY420	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY421	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY422	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY423	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY425	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY426	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY427	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY428	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY429	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY430	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY431	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY432	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY433	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY434	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY435	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY436	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY437	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY438	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY439	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY440	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY441	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY442	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY443	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY444	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY445	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY446	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY447	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY448	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY449	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY450	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY451	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY452	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY453	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY454	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY455	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY456	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY457	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY458	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY801	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY802	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY803	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY804	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY805	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY806	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY807	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY808	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY809	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY810	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY811	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY812	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY813	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY814	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY815	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY816	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY817	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY818	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY819	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY823	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY824	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY825	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY826	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY827	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY828	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY829	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY830	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY831	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY832	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY833	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY834	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY835	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY836	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY837	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY838	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY839	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A

Loc. No.	Code No.	Description ; Specification	Remark
....4 EY840	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY841	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY842	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY843	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY844	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY845	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY846	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY847	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY848	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY849	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY850	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY851	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY852	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY853	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY854	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY858	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY859	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY860	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY861	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY862	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY863	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY868	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY869	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY870	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY871	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY872	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY873	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY874	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY876	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY877	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY879	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY880	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY881	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY882	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY883	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY884	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY888	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY889	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
⚠ 4 FA801S	3601-001228	FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	
⚠ 4 FA802S	3601-001228	FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	
⚠ 4 FA803S	3601-001228	FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	
⚠ 4 FD802S	3601-000120	FUSE-AXIAL LEAD;125V,2.5A,FAST-ACTING,GL	
....4 FP801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
....4 FP801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
....4 GT403	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT404	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT405	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT406	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT801	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT804	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT805	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT809	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT810	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT811	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GT814	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 GTS01	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
....4 J105	2001-001043	R-CARBON(S);0OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4 J106	2001-001043	R-CARBON(S);0OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4 J118	2001-001043	R-CARBON(S);0OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4 J125	2001-001043	R-CARBON(S);0OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4 J127	2001-001043	R-CARBON(S);0OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4 J130	2001-001043	R-CARBON(S);0OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4 J135	2001-001043	R-CARBON(S);0OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4 J173	2001-001043	R-CARBON(S);0OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4 L302	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4 L303	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4 L406	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L407	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L409	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4 L410	2701-001032	INDUCTOR-AXIAL;100uH,10%,5x14mm	
....4 L802	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
....4 L803	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L804	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L805	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L806	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	

Loc. No.	Code No.	Description ; Specification	Remark
....4 L807	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4 L808	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4 L809	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L810	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
....4 L811	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L813	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L814	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L817	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
....4 L818	2701-001030	INDUCTOR-AXIAL;43uH,10%,5x14mm	
....4 L822	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L823	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 Q401	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q402	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 Q802	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
....4 Q803	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
....4 Q804	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 QH01	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4 QH02	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
....4 QH03	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
....4 R301	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R302	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R305	2001-001048	R-CARBON(S);1.2OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R306	2001-001163	R-CARBON(S);560OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R307	2001-001144	R-CARBON(S);4.7KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R309	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
....4 R310	2003-001018	R-METAL OXIDE(S);220ohm,5%,2W,AF,TP,3.9x	
....4 R311	2003-001018	R-METAL OXIDE(S);220ohm,5%,2W,AF,TP,3.9x	
....4 R312	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5	
....4 R313	2001-001048	R-CARBON(S);1.2OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R314	2004-004366	R-METAL(S);1.3Kohm,1%,1/2W,AA,TP,2.5x6.5	
....4 R315	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R316	2001-000356	R-CARBON;150KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R401	2008-001031	R-FUSIBLE(S);1.8ohm,5%,1W,AF,TP,3.9x10mm	
....4 R402	2001-001168	R-CARBON(S);6.8KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R403	2001-001108	R-CARBON(S);22KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R404	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R405	2003-002101	R-METAL OXIDE(S);82ohm,5%,2W,AF,TP,4x12m	
....4 R406	2001-001122	R-CARBON(S);3.9KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R407	2003-000746	R-METAL OXIDE(S);56ohm,5%,2W,AF,TP,4x12m	
....4 R408	2001-003218	R-CARBON(S);0.18ohm,10%,1/2W,AA,TP,2.4x6	
....4 R409	2003-002130	R-METAL OXIDE(S);15ohm,5%,2W,AF,TP,3.9x1	
....4 R410	2003-002101	R-METAL OXIDE(S);82ohm,5%,2W,AF,TP,4x12m	
....4 R411	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 R412	2001-001122	R-CARBON(S);3.9KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R413	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R414	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
....4 R415	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
....4 R416	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R418	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 4 R419S	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
....4 R420	2001-001093	R-CARBON(S);2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R421	2001-001106	R-CARBON(S);220KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R422	2001-001108	R-CARBON(S);22KOHM,5%,1/2W,AA,TP,2.4X6.4	
⚠ 4 R423S	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
⚠ 4 R424S	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
⚠ 4 R425S	2008-001019	R-FUSIBLE;0.2ohm,10%,1/2W,AA,TP,2.5x6.5m	
....4 R426	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
....4 R429	2004-000698	R-METAL;3.3Kohm,1%,1/4W,AA,TP,2.4x6.4m	
....4 R430	2004-001379	R-METAL(S);12Kohm,1%,1/2W,AA,TP,2.4x6.4m	
....4 R431	2004-001984	R-METAL(S);26.7Kohm,1%,1/2W,AA,TP,2.4x6.	
....4 R434	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
⚠ 4 R437S	2008-000282	R-FUSIBLE;0.47ohm,5%,1W,AA,TP,3.9x12mm	
....4 R438	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R439	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R450	2008-001022	R-FUSIBLE(S);10ohm,5%,1W,AF,TP,2.5x6.5mm	
....4 R451	2004-001390	R-METAL(S);1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
....4 R452	2001-001113	R-CARBON(S);270KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R456	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
....4 R457	2001-001159	R-CARBON(S);510OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R458	2003-000592	R-METAL OXIDE(S);22ohm,5%,2W,AF,TP,4x12m	
....4 R802	2008-000205	R-FUSIBLE(S);10ohm,5%,1/2W,AF,TP,2.5x6.5	
....4 R803	2001-001103	R-CARBON(S);20KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R804	2003-002071	R-METAL OXIDE;560ohm,5%,2W,AF,TP,3.9x10m	
....4 R805	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4 R806	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4 R807	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
....4 R808	2001-001129	R-CARBON(S);330KOHM,5%,1/2W,AA,TP,2.4X6.	

Loc. No.	Code No.	Description ; Specification	Remark
....4 R809	2001-001129	R-CARBON(S);330KOHM,5%,1/2W,AA,TP,2.4X6.	
⚠ 4 R809S	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
....4 R810	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R811	2001-000066	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R812	2009-000026	R-METAL PLATE;0.15OHM,10%,5W,CL,TP,5X14X	
....4 R813	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 R814	2001-001195	R-CARBON(S);82OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 R817	2001-001117	R-CARBON(S);2KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 R818	2001-001045	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R820	2009-000018	R-METAL PLATE;0.22ohm,10%,5W,CL,TP,5x14x	
....4 R821	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 R823	2001-001086	R-CARBON(S);18KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R824	2001-001135	R-CARBON(S);36KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R825	2001-001106	R-CARBON(S);220KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 R826	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 R827	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 R830	2001-001072	R-CARBON(S);12OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 R831	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 R834	2003-001090	R-METAL OXIDE(S);10Kohm,5%,2W,AF,TP,4x12	
....4 R835	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RH01	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RH02	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RH03	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RH04	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RH05	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RH06	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RH07	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RH08	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RH09	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
....4 RH10	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RH11	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RH12	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RH14	2001-001143	R-CARBON(S);4.3KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 RH15	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4 RH16	2001-001050	R-CARBON(S);1.5KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 RH17	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
....4 RH18	2001-001055	R-CARBON(S);1.8KOHM,5%,1/2W,AA,TP,2.4X6.	
....4 RH19	2003-002212	R-METAL OXIDE(S);75Kohm,5%,2W,AF,TP,3.9X	
....4 RH20	2003-002211	R-METAL OXIDE(S);91Kohm,5%,2W,AG,TP,3.9x	
....4 RH21	2003-002211	R-METAL OXIDE(S);91Kohm,5%,2W,AG,TP,3.9x	
....4 RH22	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RH23	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
....4 RH24	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RS01	2006-001081	R-CEMENT;82ohm,5%,5W,CJ,TP,14x10x27mm	
....4 RS02	2006-001081	R-CEMENT;82ohm,5%,5W,CJ,TP,14x10x27mm	
....4 RS03	2003-001038	R-METAL OXIDE(S);4.7ohm,5%,2W,AF,TP,3.9x	
....4 RS04	2003-001038	R-METAL OXIDE(S);4.7ohm,5%,2W,AF,TP,3.9x	
⚠ 4 RX801S	2002-001010	R-COMPOSITION;1.8Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4 RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4 VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
⚠ 4 VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
...3	AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A
..2	AA94-12596A	ASSY PCB MISC-CONTROL;CONTROL,S58A,32Z10	
...3 CNY02	AA39-00243A	LEAD CONNECTOR-ASSY;,5P,200/180MM,YBNH25	
...3 CP+KC	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...3 SWY01	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3 SWY02	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3 SWY03	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3 SWY04	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3 SWY05	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3 SWY06	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
...3	AA64-03358A	KNOB-CONTROL;32Z10,ABS,HB,G3676,SV-104M	
...3	AA97-13755A	ASSY AUTO-CONTROL;-Z6,-Z7,S58A,PAL	S.N.A
....4 0	AA41-00873A	PCB CONTROL;WS32Z10,FR-1,1,A,1.6,T,S58A,	S.N.A
....4 DZY03	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
....4 DZY04	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
....4 LY01	2701-000127	INDUCTOR-AXIAL;15uH,10%,2.5x3.4mm	
....4 RY03	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RY06	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RY07	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RY08	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4 RY09	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...3	0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2	AA94-12597A	ASSY PCB MISC-A/V SIDE;A/V SIDE,S58A,32Z	
...3 AV+HA	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...3 CN701A	AA39-20071E	LEAD CONNECTOR-ASSY;,12P,500MM,YBNH250-1	
...3 CN702A	AA39-20070F	LEAD CONNECTOR-ASSY;,7P,500,YBNH025-07,6	

Loc. No.	Code No.	Description ; Specification	Remark
...3 JA701A	3722-001164	JACK-PIN;3P,3.4mm,SN,WH:YE:RE,#16-22	
...3 JA702A	3722-000544	JACK-VHS;4P,11.5mm,AG,BLK,N	
...3 JA703A	3722-001061	JACK-PHONE;1P,3.6PI,AG,BLK,N	
...3 JA704A	3701-001013	CONNECTOR-DSUB;15P,3R,FEMALE,STRAIGHT,AU	
...3	AA97-13754A	ASSY AUTO-A/V SIDE;32Z10,S58A,EROPE	S.N.A
....4 0	AA41-00878A	PCB SUB-AV SIDE;WS32Z10,FR-1,1,A,1.6,T,S	S.N.A
....4 C703	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 C705	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 C706	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
....4 C707	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP	
....4 C708	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP	
....4 C709	2202-002008	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,50V,Y5V	
....4 C710	2202-002008	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,50V,Y5V	
....4 L701	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L702	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L703	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L704	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L705	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
....4 L706	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
....4 L707	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
⚠ 4 R704S	2001-000947	R-CARBON;7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 4 R705S	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 4 R706S	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 4 R707S	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 4 R708S	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 4 R710S	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
⚠ 4 R711S	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
...3	AA96-01365E	ASSY COVER P-HOLDER AV;32Z10,CIS,ABS HB,	S.N.A
....4	AA61-01286A	HOLDER-AV;32A10,ABS HB,G4309,SVM-1132	S.N.A
....4	AA61-30001A	LATCH-DOOR;-,-,-,-,-,-,KIFUCO LA701	
....4	AA64-00246Q	INLAY AV;32Z10,PS SHEET,T0.3	S.N.A
....4	AA64-03346A	DOOR-AV;32A10,ABS HB,G4309,SVM-1132	S.N.A
...3	0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
..2	AA94-12598A	ASSY PCB MISC-MASTER;CS34A10,S58A,32Z10,	
...3 DP811S	3711-004696	CONNECTOR-HEADER;NOWALL,3P,1R,5MM,ANGLE,	
...3 DP812S	3711-004697	CONNECTOR-HEADER;NOWALL,3P,1R,5MM,ANGLE,	
...3 HM+SW	6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
...3 PCB+HM	6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
...3 SW811S	3403-001134	SWITCH-PUSH;250V,5A,DPST,ON-OFF,-	
...3	0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
...3	AA61-00719B	HOLDER-MASTER;T6,W3,HIPS V0,BLK,J52A	S.N.A
...3	AA97-13748A	ASSY AUTO-MASTER;WS32Z10,S58A,PAL	S.N.A
....4 0	AA41-00879A	PCB-MASTER S/W;WS32Z10,CEM-1,1L,A,1.6,T,	S.N.A
....4 EY01	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY02	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY03	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4 EY04	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A

ASSY CPT

1	AA91-05786A	ASSY CPT;WS32Z6HPGX/BWT,W76QEN581X002,+3	S.N.A
⚠ ..2	AA03-00363A	CRT COLOR;W76QEN581X002,+380MG,0.302MH,6	
..2	AA27-00216A	COIL DEGAUSSING;,32INCH,10%,65TS,4.5OHM,	
..2	AA98-70011G	ASSY TBC WIRE(P);-,32inch,NTSC,2PWH,KS4A	S.N.A

ASSY COVER REAR;

1	AA90-04512B	ASSY COVER REAR;WS32Z10HVTXBWT	S.N.A
..2	AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	S.N.A
..2	AA64-03356B	CABINET BACK;32Z10,HIPS,FV2,GR503	
..2	AA63-00657A	COVER-BOSS;32Z10,HIPS,HB,G4309	S.N.A
..2	AA61-01294A	HOLDER-HANDLE,L;32Z10,HIPS HB,G4309	S.N.A
..2	AA61-01293A	HOLDER-HANDLE,R;32Z10,HIPS HB,G4309	S.N.A
..2	AA60-00091J	SPACER-FELT;-,FELT,330X10,-,-,BLK,T0.5,-	S.N.A

ASSY COVER FRONT

1	AA90-04511B	ASSY COVER FRONT;WS32Z10HVTXBWT	S.N.A
..2 CB+CF	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A

Loc. No.		Code No.	Description ; Specification	Remark
..2	CB+TER	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	CRT+CF	6006-001099	SCREW-ASS'Y TAPT;WC,HH,+,M6,L45.0,ZPC(WH	S.N.A
..2	KC+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	PP+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
..2	SPK+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2	TERRCA	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
..2	WOO+CB	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
..2		AA73-00005B	RUBBER-CAP;FLAT,PRJ,SILICONE RUBBER,WHIT	S.N.A
..2		AA96-01350B	ASSY COVER P-FRONT;WS32Z10,CIS,HIPS HB,G	S.N.A
...3	HC+CF	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
...3	INDMAS	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
...3	MAS+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
...3	SPK+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
...3	WINMAS	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
...3		AA73-00005B	RUBBER-CAP;FLAT,PRJ,SILICONE RUBBER,WHIT	S.N.A
...3		AA65-30105A	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA65-00011C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
...3		AA64-03363A	GRILLE-PS;32Z10,PS SHEET,T0.5,SVM-A245 D	S.N.A
...3		AA96-01390A	ASSY SPEAKER P;8ohm,Midrange(130*60),Twe	S.N.A
...3		AA61-01292A	HOLDER-CRT;32Z10,HIPS HB,BLK	S.N.A
...3		AA61-01292B	HOLDER-CRT;32Z10,HIPS HB,BLK	
...3		AA64-03361A	INDICATOR LED;32Z10,PC,CLR,DO	
...3		AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	S.N.A
...3		AA64-01062B	BADGE-BRAND;32Z5,AL FORGING,-,-,L65,-,SI	S.N.A
...3		AA64-03355B	CABINET FRONT;WS32Z10,HIPS,HB,G4309,SVM1	
...3		AA64-03357B	CABINET-MASK;WS32Z10,ABS,HB,G4309,SVM214	
...3		AA64-03359A	KNOB-POWER;32Z10,ABS,HB,NTR(MP0160),PLAT	
...3		AA64-03360A	WINDOW-RMC;32Z10,PC,CLR,DO	S.N.A
..2		AA96-01391A	ASSY SPEAKER P;8ohm,Midrange(50*110mm),1	S.N.A
..2		AA96-01392A	ASSY SPEAKER P;8ohm,Woofer(5inch),,25W,6	S.N.A
..2		AA96-01514A	ASSY COVER P-RACK;32Z10,CIS,ABS HB,G4309	S.N.A
...3	AHDGRA	6001-000156	SCREW-MACHINE;BH,+,M4,L8,ZPC(BLK),SM20C,	S.N.A
...3	C/R+CR	6006-001096	SCREW-ASS'Y TAPT;WP,BH,+,M4.0,L12,BLK,SW	S.N.A
...3	CASCRB	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
...3	CLATOP	6002-000522	SCREW-TAPPING;TH,+,2,M4,L15,ZPC(BLK),SWR	
...3	CRFCRB	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A
...3	CRTCRB	6002-000522	SCREW-TAPPING;TH,+,2,M4,L15,ZPC(BLK),SWR	
...3	LO+CRM	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
...3	MAGCRB	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
...3		AA91-00750A	ASSY-MAGNET,PUSH;,MAGNET,W3	
...3		AA96-01325A	ASSY COVER P-HINGE,DOOR,L;32Z10	S.N.A
...3		AA73-00005B	RUBBER-CAP;FLAT,PRJ,SILICONE RUBBER,WHIT	S.N.A
...3		AA96-01335A	ASSY COVER P-HINGE,DOOR,R;32Z10	S.N.A
...3		AA61-01332A	CASTER;32A10,SR40,NTR,W90 X D60,SR40 T2	S.N.A
...3		AA61-01332B	CASTER;32A10,NTR,SR40 T2,W90 X D60,No Ro	
...3		AA65-30101A	CLAMPER CORE-BACK;-,PE,V0,-,BLK,TOSHIBA	S.N.A
...3		AA66-00016A	ROLLER-SCREW;32Z10,LYLON,PI 19mm,WHT,M6,	S.N.A
...3		AA63-00663A	COVER-RACK-FRONT;32Z10,HIPS,HB,G4309,SVM	S.N.A
...3		AA63-00662A	COVER-RACK-MASK;32Z10,ABS,HB,G4309,SVM21	S.N.A
...3		AA61-01337A	GUIDE RAIL-ASSY R;32Z10,SECC,10,35,350	S.N.A
...3		AA61-01336A	GUIDE RAIL-ASSY L;32Z10,SECC,10,35,350	S.N.A
...3		AA61-01104A	HOLDER-LOCK;Z7,ABS	S.N.A
...3		AA61-00782B	BRACKET-MAGNET;W3,SPC,T2.0,FZW	S.N.A
...3		AA63-00664A	COVER-RACK-BODY;32Z10,HIPS,HB,G4309,DGN-	S.N.A
...3		AA69-00744F	BAG-SHEET;-,HDPE PE FOAM,T0.015,W1400,H1	S.N.A
...3		AA64-03613A	GLASS-RACK FRONT;32Z10,GLASS,T5.0,BRONZE	S.N.A
...3		AA64-03612A	GLASS-RACK;32Z10,GLASS,T8.0,CLR	S.N.A
...3		AA63-00667A	COVER-RAIL-DOOR,R;32Z10,HIPS,HB,G4309	S.N.A
...3		AA63-00666A	COVER-RAIL-DOOR,L;32Z10,HIPS,HB,G4309	S.N.A
...3		AA63-00665A	COVER-RACK-TOP;32Z10,HIPS,HB,G4309	S.N.A
..2		AA65-30017A	CLAMPER CORE-D,COIL;-,NYLON-66,V0,-,NTR,	S.N.A
..2		AA61-00813B	SUPPORT-CRT;25M6,29M6,HIPS,HB,NATURL	S.N.A
..2		AA61-00997A	HOLDER-D,COIL;32Z5,NYLON 66	S.N.A
..2		AA63-60004G	SPACER-GUM,CRT;-,NTR RUBBER,-,-,-,GRY,T3	S.N.A
..2		AA64-01334B	INLAY-CRT;ORION,PS SHEET,T1.0,50*30,-,-,	S.N.A